Tilburg University

A result on output feedback linear quadratic control

Engwerda, J.C.; Weeren, A.J.T.M.

Published in:
Automatica

Publication date:
2008

[Link to publication in Tilburg University Research Portal](#)

Citation for published version (APA):
Engwerda, J. C., & Weeren, A. J. T. M. (2008). A result on output feedback linear quadratic control. *Automatica*, 44(1), 265-271.

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

This article was published in an Elsevier journal. The attached copy is furnished to the author for non-commercial research and education use, including for instruction at the author's institution, sharing with colleagues and providing to institution administration.

Other uses, including reproduction and distribution, or selling or licensing copies, or posting to personal, institutional or third party websites are prohibited.

In most cases authors are permitted to post their version of the article (e.g. in Word or Tex form) to their personal website or institutional repository. Authors requiring further information regarding Elsevier's archiving and manuscript policies are encouraged to visit:

<http://www.elsevier.com/copyright>

Technical communiqué

A result on output feedback linear quadratic control[☆]

Jacob Engwerda^{a,*}, Arie Weeren^b

^aDepartment of Econometrics and O.R., Tilburg University, P.O. Box: 90153, 5000 LE Tilburg, The Netherlands

^bDepartment of ICT, University of Antwerp, Campus Drie Eiken, D.D209, Universiteitsplein 1, 2610 Wilrijk, Belgium

Received 20 March 2006; received in revised form 9 March 2007; accepted 10 April 2007

Available online 7 September 2007

Abstract

In this note we consider the static output feedback linear quadratic control problem. We present both necessary and sufficient conditions under which this problem has a solution in case the involved cost depends only on the output and control variables.

This result is used to present both necessary and sufficient conditions under which the corresponding linear quadratic differential game has a Nash equilibrium in case the players use static output feedback control.

Another consequence of this result is that the conditions also provide sufficient conditions for the static output stabilizability problem. Of course, in case these conditions are not met this does not mean that the system is not stabilizable via static output feedback.

© 2007 Elsevier Ltd. All rights reserved.

Keywords: LQ theory; Static output feedback controllers; Feedback stabilization; Algebraic Riccati equations; Differential games

1. Introduction

The so-called indefinite, regular, zero-endpoint, infinite-horizon LQ (IRZILQ) problem of finding a control function $u \in U_s(x_0)$ for each $x_0 \in \mathbb{R}^n$ that minimizes the cost functional

$$J(x_0, u) := \int_0^\infty (x^T Q x + u^T R u) dt, \quad (1)$$

with $Q = Q^T$, $R > 0$, and where the state variable x is the solution of $\dot{x} = Ax + Bu$, $x(0) = x_0$ has been studied by many authors (see e.g. Molinari, 1977; Trentelman & Willems, 1991; Willems, 1971 or in a more general context Grabowski, 1993). Here the class of control functions $U_s(x_0)$ is defined by

$$U_s(x_0) = \left\{ u \in L_{2,loc} \mid J(x_0, u) \text{ exists in } \mathbb{R} \cup \{-\infty, \infty\}, \lim_{t \rightarrow \infty} x(t) = 0 \right\}.$$

In van den Broek, Engwerda, and Schumacher (2003) the same problem was studied under the assumption that the class of

control functions $U_s(x_0)$ consists of the set of stabilizing, time-invariant state feedbacks, i.e. $u = Fx$ where

$$F \in \mathcal{F} := \{F \mid A + BF \text{ is stable}\}.$$

Both necessary and sufficient conditions for the existence of a solution were studied in that paper and the relationship with the (IRZILQ) problem elaborated.

However, often it is not possible or economically feasible to measure all state variables in applications. The designer wants to control the system based on the directly observed output of the system. In this note we will generalize the above problem to the output feedback setting. That is, we consider the system

$$\dot{x}(t) = Ax(t) + Bu(t), \quad x(0) = x_0, \quad y(t) = Cx(t),$$

where $x(t)$ is the unknown state variable, $y(t)$ the observations on the system, (A, B) is stabilizable, (C, A) is detectable and matrix C has full row rank. Assuming that the matrices Q and R are symmetric and R is positive definite, we want to minimize

$$J(F) = \int_0^\infty y^T(t) Q y(t) + u^T(t) R u(t) dt, \quad (2)$$

where $u(t) = Fy(t)$ and $F \in \mathcal{F} := \{F \mid \sigma(A + BFC) \subset \mathbb{C}^-\}$.

The more general case where $J(F)$ in (2) is replaced by $J(F) := \int_0^\infty x^T(t) Q x(t) + u^T(t) R u(t) dt$ has been already

[☆] This paper was not presented at any IFAC meeting. This paper was recommended for publication in revised form by Associate Editor Jay H. Lee under the direction of Editor Andre Tits.

* Corresponding author. Tel.: +31 134662174; fax: +31 134663280.

E-mail addresses: engwerda@uvt.nl (J. Engwerda), arie.weeren@ua.ac.be (A. Weeren).

studied in literature by various authors (see e.g. Levine & Athans, 1970; Rekasius, 1967; Zheng, 1989). However, both necessary and sufficient conditions for solving this output feedback control problem in its original form had not been provided. In Section 2, we show that for the restricted problem it is possible to provide both necessary and sufficient conditions. This result can then immediately be used to formulate also conditions under which the corresponding game problem has a solution, which is performed in Section 3. Finally, Section 4 contains some concluding remarks.

2. The one-player case

Before we present the main result of this note, we first introduce some notation.

If $\mathcal{X}$ and $\mathcal{Y}$ are finite-dimensional vector spaces and $\mathcal{D}$ is an open subset of $\mathcal{X}$, we denote the derivative of a differentiable map $T : \mathcal{D} \rightarrow \mathcal{Y}$ by ∂T and the differential of T at $x \in \mathcal{D}$ in the direction h by $\delta T(x; h)$. We have $\delta T(x; h) = \partial T(x)h$ (see e.g. Luenberger, 1969, Chapter 7). Partial derivatives and differentials are denoted by ∂_i and δ_i where the index refers to the corresponding argument.

Furthermore, the next algebraic Riccati equation will play an important role in the analysis below:

$$A^T P + PA - PBR^{-1}B^T P + C^T Q C = 0. \quad (3)$$

We have the following result:

Theorem 2.1. Assume that there exist P and F^* such that $X := P$ solves (3) with $\sigma(A - BR^{-1}B^T X) \subset \mathbb{C}^-$ and $R^{-1}B^T X = -F^*C$. Then $\min_F J(F)$ exists for all x_0 and is attained by $F = F^*$. Moreover, $J(F^*) = x_0^T X x_0$.

Conversely, if $\min_{F \in \mathcal{F}} J(F)$ exists for all x_0 , then there exist matrices X and F^* such that $P := X$ satisfies (3), $\sigma(A - BR^{-1}B^T X) \subset \mathbb{C}^-$ and $R^{-1}B^T X = -F^*C$.

Proof. “ $\Rightarrow$ part”: Let $F \in \mathcal{F}$. Then, with $x_F(t) = e^{(A+BFC)t}x_0$,

$$\begin{aligned} J &= \int_0^\infty \{x_F^T(t)[C^T Q C + C^T F^T R F C]x_F(t) \\ &\quad + \dot{x}_F^T(t)X x_F(t) + x_F^T(t)X \dot{x}_F(t)\} dt + x_0^T X x_0 \\ &= \int_0^\infty \{x_F^T(t)[C^T Q C + C^T F^T R F C]x_F(t) \\ &\quad + x_F^T(t)(A + BFC)^T X x_F(t) \\ &\quad + x_F^T(t)X(A + BFC)x_F(t)\} dt + x_0^T X x_0 \\ &= \int_0^\infty \{x_F^T(t)[A^T X + XA + C^T Q C + C^T F^T R F C \\ &\quad + C^T F^T B^T X + X B F C]x_F(t)\} dt + x_0^T X x_0 \\ &= \int_0^\infty \{x_F^T(t)[X B R^{-1} B^T X + C^T F^T R F C \\ &\quad + C^T F^T B^T X + X B F C]x_F(t)\} dt + x_0^T X x_0 \\ &= \int_0^\infty \{x_F^T(t)[C^T F^{*T} R F^* C + C^T F^T R F C \\ &\quad - C^T F^T R F^* C - C^T F^{*T} R F C]x_F(t)\} dt + x_0^T X x_0 \\ &= \int_0^\infty \{x_F^T(t)C^T(F^{*T} - F^T)R(F^* - F)C x_F(t)\} dt + x_0^T X x_0. \end{aligned}$$

From this it is clear that $J(F) \geq x_0^T X x_0$ and that equality is obtained by choosing $F = F^*$. Note that since C is full row rank this choice is uniquely determined.

“ $\Leftarrow$ part”: This part of the proof is based on a variational argument. First, note that the set $\mathcal{F}$ is a nonempty open set. Second, note that the smoothness of the coefficients in a Lyapunov equation is preserved by the solution of this equation (see e.g. Lancaster & Rodman, 1995, Section 5.4), which implies that J is differentiable with respect to F . Now, let $F^* \in \mathcal{F}$ be a minimum of J for each x_0 . Then, $\delta_2 J(x_0, F^*; \Delta F) = 0$ for each ΔF and for each x_0 . Notice that for all $F \in \mathcal{F}$,

$$J(F) = x_0^T \int_0^\infty e^{(A+BFC)^T t} [C^T Q C + C^T F^T R F C] \times e^{(A+BFC)t} dt x_0 \quad (4)$$

$$=: x_0^T \varphi(F) x_0. \quad (5)$$

So in particular it follows that $\delta \varphi(F^*; \Delta F) = 0$ for all increments ΔF . Hence

$$\partial \varphi(F^*) = 0. \quad (6)$$

Next, introduce the map $\Phi : \mathcal{F} \times \mathbb{R}^{n \times n} \rightarrow \mathbb{R}^{n \times n}$ by

$$\begin{aligned} \Phi(F, P) &= (A + BFC)^T P + P(A + BFC) + C^T Q C \\ &\quad + C^T F^T R F C. \end{aligned}$$

Using (4), (5) we have that

$$\begin{aligned} &-(C^T Q C + C^T F^T R F C) \\ &= \int_0^\infty \left\{ \frac{d}{dt} [e^{(A+BFC)^T t} [C^T Q C \right. \\ &\quad \left. + C^T F^T R F C] e^{(A+BFC)t}] \right\} dt \\ &= (A + BFC)^T \varphi(F) + \varphi(F)(A + BFC). \end{aligned}$$

So, $\Phi(F, \varphi(F)) = 0$ for all $F \in \mathcal{F}$. Taking the derivative of this equality and applying the chain rule yields

$$\partial_1 \Phi(F, \varphi(F)) + \partial_2 \Phi(F, \varphi(F)) \partial \varphi(F) = 0 \quad \text{for all } F \in \mathcal{F}.$$

Substituting $F = F^*$ in this equality, and using (6), shows that $\partial_1 \Phi(F^*, \varphi(F^*)) = 0$, or, equivalently,

$$\delta_1 \Phi(F^*, \varphi(F^*); \Delta F) = 0 \quad \text{for all } \Delta F. \quad (7)$$

The differential of Φ with respect to its first argument with increment ΔF is

$$\delta_1 \Phi(F, P; \Delta F) = C^T \Delta F^T (B^T P + R F C) + (P B + C^T F^T R) \Delta F C.$$

Combining this result with (7) produces

$$C^T \Delta F^T (B^T \varphi(F^*) + R F^* C) + (\varphi(F^*) B + C^T F^{*T} R) \Delta F C = 0 \quad \text{for all } \Delta F.$$

Since C is full row rank, the above equality implies that $B^T \varphi(F^*) + R F^* C = 0$, or, equivalently, $F^* C = -R^{-1} B^T \varphi(F^*)$. Now, since $\Phi(F^*, \varphi(F^*)) = 0$ and $F \in \mathcal{F}$, we conclude that $X := \varphi(F^*)$ is the stabilizing solution of the ARE (3). $\square$

Remark 2.2. (1) Since matrix C is full row rank it follows directly from Theorem 2.1 that in case the optimization problem has a solution, the optimal feedback is unique and given by $F^* = -R^{-1}B^T X C^T (C C^T)^{-1}$.

(2) If matrix C is invertible the optimal feedback coincides with the one that is obtained from the IRZILQ problem. For if C is invertible, the observed variable y satisfies the differential

$$\begin{bmatrix} A^T(L - G^+GLBB^+) + (L - G^+GLBB^+) + C^TQC & (L - G^+GLBB^+)B \\ B^T(L - G^+GLBB^+) & R \end{bmatrix} \geq 0.$$

equation

$$\dot{y}(t) = CAC^{-1}y(t) + CBu(t).$$

So the optimal control minimizing J is: $u^*(t) = -R^{-1}B^T C^T X y(t)$, where X is the stabilizing solution of the algebraic Riccati equation

$$(CAC^{-1})^T X + XCAC^{-1} - XCBR^{-1}B^T C^T X + Q.$$

With $\tilde{X} := C^T X C$ it is then easily verified that X satisfies the above equation if and only if $\tilde{X}$ satisfies the algebraic Riccati equation (3). Furthermore it is obvious that $u^*(t)$ can be rewritten as $u^*(t) = -R^{-1}B^T C^T \tilde{X} C^{-1} y(t)$, which is precisely the optimal control from Theorem 2.1 (see item (1) of this remark).

Remark 2.3. (1) In applications usually the solvability condition for the output feedback problem has to be verified numerically. So the question arises as to how one can verify in a numerically reliable way the condition that some part of the column space of the stabilizing solution X of the Riccati equation (3) is contained in some subspace. In general, this is a difficult problem. For that reason the question remains whether it is possible to find more directly verifiable conditions under which the output feedback problem has a solution.

We will briefly indicate two ways how one might proceed numerically. However, it remains a topic for future research to see whether there exist numerically more reliable procedures to test the presented solvability condition.

The most simple and direct way is to calculate first the stabilizing solution X of (3), using e.g. Matlab (this step might be preceded by a step in which one verifies whether a stabilizing solution exists for this equation by verifying whether the corresponding Hamiltonian matrix has a stable invariant graph subspace). The next step is then to verify whether the set of linear equations

$$R^{-1}B^T X = -F C \quad (8)$$

has a solution F . One may either verify this directly (using e.g. Matlab again) or by noting that, with $G := I - C^T (C C^T)^{-1} C$, (8) has a solution if and only if

$$G X B R^{-1} = 0 \quad \text{or} \quad G X B = 0. \quad (9)$$

Another way one might proceed is by including the restriction (8) directly in the LMI associated with (3). All solutions X of (9) are: $\{L - G^+GLBB^+ \mid L \in \mathbb{R}^{n \times n}\}$. Here H^+ is the Moore-Penrose inverse of matrix H (see e.g. Abadir & Magnus, 2005).

Therefore the output feedback problem has a solution if and only if the next LMI has a solution L such that $X := L - G^+GLBB^+$ is symmetric and $\sigma(A - BR^{-1}B^T X) \subset \mathbb{C}^-$ (see e.g. Willems, 1971 for more details)

(2) In addition to point (1) notice that in case the conditions of Theorem 2.1 are only approximately met, i.e. there exist P , F^* , ε_1 and ε_2 (where the last two matrices are small) such that

$$\begin{aligned} A^T P + PA - PBR^{-1}B^T P + C^T Q C &= \varepsilon_1 \quad \text{and} \\ R^{-1}B^T P &= -F^* C + \varepsilon_2, \end{aligned}$$

for an arbitrary static output feedback control $u(t) = Fx(t)$ (where F may depend on e.g. the initial state of the system) we have that

$$\begin{aligned} J &= \int_0^\infty \{x_F^T(t) [C^T(F^{*T} - F^T) - \varepsilon_2^T] \\ &\quad \times R[(F^* - F)C - \varepsilon_2] + \varepsilon_1\} x_F(t) dt + x_0^T X x_0. \end{aligned}$$

This can be verified similar to the proof of Theorem 2.1. From this it is clear that $J(F) \approx x_0^T X x_0$ and that equality is approximately obtained by choosing $F = F^*$.

(3) If matrix B is invertible the computational efforts in verifying the existence of a solution can be reduced. In that case the problem has a solution if and only if $X = C^T P C$ for some symmetric matrix P . Consequently the problem has a solution if and only if there exists a symmetric matrix P such that

$$\begin{aligned} A^T C^T P C + C^T P C A - C^T P C B R^{-1} B^T C^T P C + C^T Q C &= 0 \\ \text{with } \sigma(A - B R^{-1} B^T C^T P C) &\subset \mathbb{C}^-. \end{aligned} \quad (10)$$

Since by assumption C is full row rank, this equation only has a solution if the next ordinary Riccati equation (which dimension is smaller) has the stabilizing solution P

$$\begin{aligned} (C C^T)^{-1} C A^T C^T P + P C A C^T (C C^T)^{-1} \\ - P C B R^{-1} B^T C^T P + Q &= 0. \end{aligned} \quad (11)$$

So, by first determining the stabilizing solution P from (11) and next verifying whether this solution satisfies (10) calculation speed can be improved.

Before we proceed with some examples we first notice that the output feedback problem has a solution if and only if using any state and/or input transformation the corresponding output feedback problem has a solution w.r.t. these new coordinates. So, without loss of generality, one may assume e.g. (see Example 2.4) that the system is posed in terms of its observable canonical form.

Example 2.4. Consider the optimal control problem to find the minimum w.r.t. f for all $x_0 \in \mathbb{R}^n$ of

$$J(f) = \int_0^\infty y^2(t) + u^2(t) dt,$$

where $u(t) = fy(t)$ with $f \in \mathcal{F}$, subject to the system

$$\begin{aligned} \dot{x}(t) &= \begin{bmatrix} 0 & -a_n & 0 & \cdots & \cdots & 0 \\ 1 & 0 & -a_{n-1} & 0 & \cdots & 0 \\ 0 & 1 & 0 & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & \ddots & \ddots & 0 \\ 0 & \cdots & 0 & 1 & 0 & -a_2 \\ 0 & \cdots & \cdots & 0 & 1 & -a_1 \end{bmatrix} x(t) + bu(t), \\ x(0) &= x_0, \quad y(t) = [0 \cdots 0 \ 1]x(t), \end{aligned} \quad (12)$$

where $a_1 \neq 0$ and (A, b) is stabilizable.

According to Theorem 2.1, with $P := [p_{ij}]$ the stabilizing solution of the algebraic Riccati equation (3), this problem has a solution only if the next condition is satisfied

$$b^T P = -f[0 \cdots 0 \ 1].$$

Using this, the algebraic Riccati equation (3) reduces to

$$A^T P + PA - \begin{bmatrix} 0 & \cdots & \cdots & 0 \\ \vdots & \ddots & & \vdots \\ 0 & \cdots & 0 & 0 \\ 0 & \cdots & 0 & (b^T P_{,n})^2 - 1 \end{bmatrix} = 0.$$

Since the system is both stabilizable and observable this algebraic Riccati equation has a positive definite solution (see, e.g. Lancaster & Rodman, 1995, Proposition 16.2.8). Using this, straightforward (but lengthy) induction arguments show that the above equation has a solution only if $a_i > 0$, $i > 1$ and $p_{ij} = 0$, $i \neq j$ and $p_{ii} = a_{n-i+2}p_{i-1,i-1}$, $i = 2, \dots, n$. Consequently, with $b^T := [b_n, \dots, b_1]$ and $p := p_{11}$,

$$b^T P = [b_n p \ b_{n-1} a_n p \ \cdots \ b_1 a_2 \cdots a_n p].$$

From this it is then easily verified that the output feedback problem has a solution if and only if $a_i > 0$ and $b_i = 0$ for $i > 1$. Furthermore the appropriate output feedback gain f is in that case

$$f = -b_1 a_2 \cdots a_n p \quad \text{with } p = \frac{-a_1 + \sqrt{a_1^2 + b_1^2}}{b_1^2 a_2 \cdots a_n}.$$

Finally, notice that not every SISO observable system can be rewritten in the form (12). However, using a state transformation S (where S is upper triangular with all its main diagonal entries $-a_1$ and all even subdiagonal entries zeros) generically one can transform the standard state canonical

observable system with

$$A := \begin{bmatrix} 0 & 0 & 0 & \cdots & \cdots & -v_n \\ 1 & 0 & 0 & 0 & \cdots & -v_{n-1} \\ 0 & 1 & 0 & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & \ddots & \ddots & 0 \\ 0 & \cdots & 0 & 1 & 0 & -v_2 \\ 0 & \cdots & \cdots & 0 & 1 & -a_1 \end{bmatrix} \quad \text{and} \\ C := [0 \cdots 0 \ 1],$$

into the form (12) under the assumption that $a_1 \neq 0$.

Example 2.5. Assume $Q > 0$. The output feedback problem has a solution in the next two cases.

(i) $A = \begin{bmatrix} A_{11} & 0 \\ A_{12} & A_{22} \end{bmatrix}$, $B = \begin{bmatrix} B_1 \\ B_2 \end{bmatrix}$, $C = [C_1 \ 0]$, with C_1 invertible, A_{22} stable and (A_{11}, B_1) stabilizable.

By choosing $X = \begin{bmatrix} X_1 & 0 \\ 0 & 0 \end{bmatrix}$, where X_1 is the stabilizing solution of the algebraic Riccati equation

$$A_{11}^T X_1 + X_1 A_{11} - X_1 B_1 R^{-1} B_1^T X_1 + C_1^T Q C_1 = 0, \quad (13)$$

it is easily verified that both (3) and the equation $R^{-1} B^T X = -FC$ have an appropriate solution.

(ii) $A = \begin{bmatrix} A_{11} & A_2 \\ -\alpha A_2^{-1} & 0 \end{bmatrix}$, $B = \begin{bmatrix} B_1 \\ 0 \end{bmatrix}$, $C = [C_1 \ 0]$, with C_1 invertible, A_2 invertible, $\alpha > 0$ and (A_{11}, B_1) stabilizable.

Straightforward calculations show that with $X = \begin{bmatrix} X_1 & 0 \\ 0 & X_3 \end{bmatrix}$, where X_1 is the stabilizing solution of (13) again and $X_3 = \alpha A_2^T X_1 A_2$, both (3) and the equation $R^{-1} B^T X = -FC$ have a solution. Furthermore, the property that $A_{cl} := A - BR^{-1} B^T X$ is a stable matrix follows by noticing that the inertia of matrix $GA_{cl}G^T$, with $G := \begin{bmatrix} \alpha A_2^{-1} A_{cl}^{-1} & -I \\ -I & 0 \end{bmatrix}$, coincide with those of $\alpha A_2^{-1} A_{cl}^{-1} A_2 \cup A_{cl}$, from which the claim is obvious.

(iii) The output feedback problem has no solution if (A, B) is stabilizable, $(C\sqrt{Q}, A)$ observable and $CB = 0$.

This follows since the stabilizing solution, X , of (3) is positive definite under these assumptions (see Lancaster & Rodman, 1995, Proposition 16.2.8). Therefore $B^T X B > 0$. However, if an output feedback solution exists, then it follows that $-R^{-1} B^T X B = FC B = 0$. That is, $B^T X B = 0$.

Example 2.6. This example provides a case where a feedback which is simultaneously optimal for all initial states does not exist, though for every initial state there exists an optimal feedback (depending on the initial state).

Consider the optimal control problem to find for a fixed initial state the minimum w.r.t. f for

$$J(f) = \int_0^\infty y^2(t) + u^2(t) dt,$$

where $u(t) = fy(t)$ with $f \in \mathcal{F}$, subject to the system

$$\begin{aligned} \dot{x}(t) &= \begin{bmatrix} -1 & 1 \\ 0 & -2 \end{bmatrix} x(t) + \begin{bmatrix} 1 \\ 0 \end{bmatrix} u(t), \\ x(0) &= x_0, \quad y(t) = [1 \ 0]x(t). \end{aligned}$$

Notice that this system is not controllable. Now, let $P = [p_{ij}]$ be a corresponding solution of (3) with this problem. Since

Fig. 1. Optimal f as a function of the angle θ for Example 2.4.

$[1 \ 0]P = -f[1 \ 0]$ should hold it follows that $p_{12} = 0$. Using this it follows then by an elementary spelling of (3) that it does not have a solution. So this control problem does not have an output feedback which is optimal for every initial state.

Let $x(t) = [x_1(t) \ x_2(t)]^T$ and $x_0 = [\alpha \ \beta]$. Elementary calculations show then that with $f \in \mathcal{F}$,

$$x_1(t) = \begin{cases} \left(\alpha + \frac{\beta}{f+1} \right) e^{(f-1)t} - \frac{\beta}{f+1} e^{-2t}, & f \neq -1; \\ \alpha e^{-2t} + \beta t e^{-2t}, & f = -1. \end{cases}$$

Therefore, for $f \neq -1$,

$$\begin{aligned} J(f) &= (1+f^2) \int_0^\infty x_1^2(t) dt = -(1+f^2) \\ &\quad \times \left[\frac{(\alpha(f+1)+\beta)^2}{2(f+1)^2(f-1)} - \frac{2\beta(\alpha(f+1)+\beta)}{(f+1)^2(f-3)} - \frac{\beta^2}{4(f+1)^2} \right] \\ &= \frac{-(1+f^2)}{4(f-1)(f-3)} [2\alpha^2(f-1) - (2\alpha+\beta)^2]. \end{aligned}$$

Whereas $J(-1) = 2[\frac{1}{4}\alpha^2 + \frac{1}{8}\alpha\beta + \frac{1}{32}\beta^2]$.

From this it follows in particular that $J(f)$ is differentiable on $(-\infty, 1)$. Straightforward differentiation yields then that, with $\gamma := 2 + \beta/\alpha$,

$$J'(f) = \frac{-\alpha^2[f^4 - 8f^3 + (2\gamma^2 + 12)f^2 - (2\gamma^2 + 4)f - (2\gamma^2 + 1)]}{(f-1)^2(f-3)^2}.$$

Obviously, $J'(f)$ is continuous on $(-\infty, 1)$. Furthermore it is clear that $\lim_{f \rightarrow -\infty} J'(f) < 0$, whereas $\lim_{f \uparrow 1} J'(f) > 0$. So, $J(f)$ has a global minimum on $(-\infty, 1)$. Furthermore it can be verified, using e.g. a numerical symbolic toolbox, that the location where this minimum is attained depends on the choice of γ , that is on x_0 . Using polar coordinates we plotted in Fig. 1 the optimal f as a function of the angle θ . Since $J'(f)$ only depends on γ it is clear that the optimal f does not depend on the radius r in this example.

Remark 2.7. The fact that in the previous example the optimal f is the same for every initial state on a line through the origin is not a coincidence. This property holds in general. For, if F minimizes $J(F, x_0) = x_0^T \int_0^\infty e^{(A+BFC)^T t} (Q + F^T R F) e^{(A+BFC)t} dt x_0$ then, obviously, it also minimizes $J(F, \lambda x_0) = \lambda^2 J(F, x_0)$.

Finally, the next example shows (see also Trentelman, 1989) that there also exist cases where the problem has no solution for every initial state (even though $J(f)$ has an infimum).

Example 2.8. Consider the optimal control problem to find for a fixed initial state the minimum w.r.t. $f \in \mathcal{F}$ for

$$J(f) = \int_0^\infty -y^2(t) + u^2(t) dt,$$

where $u(t) = f y(t)$ with $f \in \mathcal{F}$, subject to the system

$$\dot{x}(t) = -x(t) + u(t), \quad x(0) = x_0, \quad y(t) = x(t).$$

Straightforward calculations show that

$$\begin{aligned} J(f) &= (-1 + f^2) \int_0^\infty x^2(t) dt \\ &= (-1 + f^2) x_0^2 \int_0^\infty e^{2(-1+f)t} dt \\ &= \frac{1-f^2}{2(f-1)} x_0^2 = \frac{-1}{2} (1+f) x_0^2. \end{aligned}$$

Since $\mathcal{F} = \{f \mid f < 1\}$ it is clear from the last equality that, for $x_0 \neq 0$, $J(f)$ has not a minimum in $\mathcal{F}$, although the infimum exists for any such initial state and is $-x_0^2$.

Since the cost function promotes large values of y , whereas on the other hand the controller is constrained to be stabilizing the outcome of this example is not surprising.

3. An application to LQ differential games

In this section we use the equivalence result from Theorem 2.1 to characterize output feedback Nash equilibria in infinite-horizon LQ differential games.

The following notation will be used. For an N -tuple $\hat{F} = (\hat{F}_1, \dots, \hat{F}_N) \in \Gamma_1 \times \dots \times \Gamma_N$ for given sets Γ_i , we shall write $\hat{F}_{-i}(\alpha) = (\hat{F}_1, \dots, \hat{F}_{i-1}, \alpha, \hat{F}_{i+1}, \dots, \hat{F}_N)$ with $\alpha \in \Gamma_i$.

Consider the cost function of player i defined by

$$J_i(x_0, F_1, \dots, F_N) = \int_0^\infty \left(y_i^T Q_i y_i + \sum_{j=1}^N u_j^T R_{ij} u_j \right) dt$$

with $u_j = F_j y_j$ for $j = 1, \dots, N$, and where x is generated by

$$\dot{x}(t) = Ax(t) + \sum_{j=1}^N B_j u_j(t) \quad x(0) = x_0 \quad \text{and} \quad y_i(t) = C_i x(t).$$

Assume that Q_i is symmetric, R_{ii} is positive definite, C_i is full row rank and $(F_1, \dots, F_N) \in \mathcal{F}_N$, where

$$\mathcal{F}_N = \left\{ (F_1, \dots, F_N) \left| A + \sum_{j=1}^N B_j F_j C_j \text{ is stable} \right. \right\}. \quad (14)$$

This last assumption spoils the rectangular structure of the strategy spaces, i.e. choices of feedback matrices cannot be made independently. However, such a restriction is motivated by the fact that closed-loop stability is usually a common objective.

In our setting the concept of an output feedback Nash equilibrium is defined as follows.

Definition 3.1. An N -tuple $\hat{F} = (\hat{F}_1, \dots, \hat{F}_N) \in \mathcal{F}_N$ is called an *output feedback Nash equilibrium* if for all i the following inequality holds:

$$J_i(x_0, \hat{F}) \leq J_i(x_0, \hat{F}_{-i}(\alpha))$$

for each x_0 and for each matrix α such that $\hat{F}_{-i}(\alpha) \in \mathcal{F}_N$.

Next, consider the set of coupled algebraic Riccati equations:

$$\begin{aligned} A^T X_i + X_i A - \sum_{j=1, j \neq i}^N X_i B_j R_{jj}^{-1} B_j^T X_j \\ - \sum_{j=1, j \neq i}^N X_j B_j R_{jj}^{-1} B_j^T X_i - X_i B_i R_{ii}^{-1} B_i^T X_i \\ + \sum_{j=1, j \neq i}^N X_j B_j R_{jj}^{-1} R_{ij} R_{jj}^{-1} B_j^T X_j + C_i^T Q_i C_i = 0, \\ i = 1, \dots, N. \end{aligned} \quad (15)$$

A *stabilizing solution* of (15) is an N -tuple $(X_1, \dots, X_N)$ of real symmetric $n \times n$ matrices satisfying (15) such that $A - \sum_{j=1}^N B_j R_{jj}^{-1} B_j^T X_j$ is stable. In contrast to the stabilizing solution of (3), stabilizing solutions of (15) are not necessarily unique (see e.g. Engwerda, 2005). The next theorem states that output feedback Nash equilibria are completely characterized by stabilizing solutions of (15) satisfying some important constraint. Its proof follows directly from Theorem 2.1 (see also the proof of Engwerda, 2005, Theorem 8.5).

Theorem 3.2. Let $(X_1, \dots, X_N)$ be a stabilizing solution of (15) and $(F_1, \dots, F_N)$ be such that $R_{ii}^{-1} B_i^T X_i = -F_i C_i$ for $i = 1, \dots, N$. Then $(F_1, \dots, F_N)$ is an output feedback Nash equilibrium. Conversely, if $(F_1, \dots, F_N)$ is an output feedback Nash equilibrium, there exists a stabilizing solution $(X_1, \dots, X_N)$ of (15) and $(F_1, \dots, F_N)$ such that $R_{ii}^{-1} B_i^T X_i = -F_i C_i$.

Furthermore, if the game has an output feedback Nash equilibrium with this equilibrium the corresponding cost for player i is $J_i(x_0, \hat{F}) = x_0^T X_i x_0$.

4. Concluding remarks

In this note we considered the LQ static output feedback problem for a special type of cost functional. The cost function is special in the sense that apart from the controls just the observed output variables are taken into account. Following the analysis of van den Broek et al. (2003) (see also Engwerda, 2005) we derived both necessary and sufficient conditions for this problem under which there exists a solution.

The conditions under which a solution exists are in general rather strict. That is, in general a static output feedback control that will be optimal for every initial state will not exist. We illustrated this in some examples. Moreover, we showed in an example that in case for all initial states the same output feedback is not optimal it may still be possible that for every initial state there exists an optimal (initial state dependent) output feedback.

The existence conditions for a solution of the problem are stated in terms of the stabilizing solution of an algebraic Riccati equation. An open problem that remains is to find conditions on the system parameters under which one can directly verify (without first calculating the solution of this Riccati equation) whether the problem will have a solution.

Finally, the one-player result was used to find both necessary and sufficient conditions for the existence of an output feedback Nash equilibrium. The presented conditions are phrased in terms of the existence of a stabilizing solution of a set of coupled algebraic Riccati equation. Like in the full state observation case it remains in particular an open question under which conditions this set of equations will have a unique stabilizing solution.

Acknowledgements

The authors like to thank the referees and Hans Schumacher for their comments on a previous draft of the paper.

References

- Abadir, K. M., & Magnus, J. R. (2005). *Matrix algebra*. Cambridge: Cambridge University Press.
- van den Broek, W. A., Engwerda, J. C., & Schumacher, J. M. (2003). An equivalence result in linear-quadratic theory. *Automatica*, 39, 355–359.
- Engwerda, J. C. (2005). *LQ dynamic optimization and differential games*. Chichester: Wiley.
- Grabowski, P. (1993). The LQ controller synthesis problem. *IMA Journal of Mathematical Control and Information*, 10, 131–148.
- Lancaster, P., & Rodman, L. (1995). *Algebraic riccati equations*. Oxford: Oxford University Press.
- Levine, W. S., & Athans, M. (1970). On the determination of the optimal constant output feedback gains for linear multivariable systems. *IEEE Transactions on Automatic Control*, 15, 44–48.
- Luenberger, D. G. (1969). *Optimization by vector space methods*. New York: Wiley.
- Molinari, B. P. (1977). The time-invariant linear-quadratic optimal control problem. *Automatica*, 13, 347–357.
- Rekasius, Z. V. (1967). Optimal linear regulators with incomplete state feedback. *IEEE Transactions on Automatic Control*, 12, 296–299.

- Trentelman, H. L. (1989). The regular free-endpoint linear quadratic problem with indefinite cost. *SIAM Journal Control and Optimization*, 27, 27–42.
- Trentelman, H. L., & Willems, J. C. (1991). The dissipation inequality and the algebraic Riccati equation. In S. Bittanti, A. J. Laub, & J. C. Willems (Eds.), *The Riccati equation* (pp. 197–242). Berlin: Springer.
- Willems, J. C. (1971). Least squares stationary optimal control and the algebraic Riccati equation. *IEEE Transactions on Automatic Control*, 16, 621–634.
- Zheng, D.-Z. (1989). Some new results on optimal and suboptimal regulators of the LQ problem with output feedback. *IEEE Transactions on Automatic Control*, 34, 557–560.