Tilburg University

Performance evaluation of polling systems by means of the power-series algorithm

Blanc, J.P.C.

Publication date:
1990

[Link to publication in Tilburg University Research Portal](#)

Citation for published version (APA):

Blanc, J. P. C. (1990). *Performance evaluation of polling systems by means of the power-series algorithm*. (Research memorandum / Tilburg University, Department of Economics; Vol. FEW 459). Unknown Publisher.

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

CBM

CBM
R

7626
1990
459

UNIVERSITEIT
BRABANT

POSTBOX 90153
5000 LE TILBURG
THE NETHERLANDS

DEPARTMENT OF ECONOMICS
RESEARCH MEMORANDUM

PERFORMANCE EVALUATION OF POLLING
SYSTEMS BY MEANS OF THE POWER-SERIES
ALGORITHM

J.P.C. Blanc

FEW 459

PERFORMANCE EVALUATION OF POLLING SYSTEMS
BY MEANS OF THE POWER-SERIES ALGORITHM

J.P.C. Blanc

Tilburg University, Faculty of Economics
P.O. Box 90153, 5000 LE Tilburg, The Netherlands

Abstract

A general description is given of the power-series algorithm for the performance evaluation of multi-queue systems which can be modeled as multi-dimensional quasi-birth-death processes. The complexity of the algorithm when applied to polling systems, consisting of several stations where jobs are generated and a single server which attends to these stations by turns, is studied for various service disciplines. The algorithm is applied to a general class of polling systems with Poisson arrival streams, with Coxian service and switching time distributions, with infinite buffers, with a fixed periodic visit order, and with a Bernoulli schedule for each visit to a station.

Keywords: polling table, Bernoulli schedule, waiting time.

1. Introduction

The power-series algorithm (p.s.a.) is a new tool for the performance evaluation of moderately sized multi-queue systems which can be modeled as multi-dimensional quasi-birth-death processes. Such processes consist of a vector of components which describe the number of jobs in each queue, and possibly one or more supplementary components with a finite range, which may be used, for instance, to model Coxian service time distributions. An important class of systems which can be modeled by such a process is that of polling systems. By polling systems we mean single-server multi-queue systems in which the server visits the queues according to some static or dynamic rule (service discipline) and in which the times required for switching service from one queue to another may be non-negligible. Polling systems are widely used to model computer-communication networks with a single transmission channel and a collision-free access protocol, cf. Takagi [22,23]. More generally, they can be used to model systems in which several classes of jobs compete for service by a single server.

Only few exact results have been obtained for polling systems. The most general type of results consists of pseudo-conservation laws, expressions for a weighted sum of the mean waiting times at the various queues, cf. Boxma [9]. More detailed results have only been obtained for polling systems with specific service disciplines such as fixed priorities attached to the queues, cf. Jaiswal [17], Klimov & Mishkoy [18], and periodic polling orders with either exhaustive or gated service at each queue, cf. Cooper [15], Baker & Rubin [1], Sarkar & Zangwill [20]. Therefore, it is useful to develop algorithms for the numerical evaluation of queueing characteristics for a more general class of polling systems. The basic idea of the p.s.a. is the transformation of the non-recursively solvable (infinite) set of balance equations for the stationary state probabilities into an, in principle, recursively solvable set of equations by adding one dimension to the state space. This transformation is realized by means of power-series expansions of the state probabilities as functions of the occupancy (load) of a system in light traffic. The basic idea of the p.s.a. has been introduced in Hooghiemstra et al. [16]. The algorithm has been further developed in Blanc [3,4,5,6,8], which has led to more efficient implementations of the algorithm, faster convergence of the power series by means of the epsilon algorithm, cf. Wynn [25], especially when the occupancy of a system is high, and a broader scope of applications for the

algorithm. The p.s.a. has been applied to several types of multi-queue models such as the shortest-queue model (Blanc [2,6]), the coupled-processor model (Hooghiemstra et al. [16], Blanc [4]), and some polling models (Blanc [5,7,8]). The p.s.a. provides accurate data for moderate sized systems, which are of interest in itself for studying the interaction between queues, and which may be helpful in finding and validating approximations for large scale systems.

The present paper aims to give a general description of the principle and the applicability of the p.s.a. (section 2), to discuss the complexity of the computations of the p.s.a. when applied to polling systems with various service disciplines (section 3), and to consider the p.s.a. in more detail for polling systems with Poisson arrival streams, with Coxian service and switching time distributions, with a general periodic visit order, and with a Bernoulli schedule for each visit to a station (section 4), thereby extending the results obtained in Blanc [8]. Potential further extensions of the models and the algorithm will be discussed in section 5.

2. The power-series algorithm

The p.s.a. will be discussed in the following sections for a general class of models. Topics include conditions for application of the algorithm, means for accelerating the convergence of the series and notes on implementation of the algorithm.

2.1. Description of the Markov process

Consider the following class of multi-dimensional quasi-birth-death processes. The process consists of an s -dimensional vector $\bar{N} := (N_1, \dots, N_s)$ and a supplementary variable F . The components of the vector $\bar{N}$, which describe the number of jobs in the various queues in steady state, take non-negative integer values, and the variable F may take a finite number of values, say in the set Θ . In fact, the supplementary space does not need to be the same for each $\bar{n} \in \mathbb{N}^s$. However, the maximum of the sizes of these spaces over all $\bar{n}, \bar{n} \in \mathbb{N}^s$, should be finite. For simplicity of the discussion we will assume that the supplementary space is the same for each $\bar{n}$, while it is possible that some states $(\bar{n}, \varphi)$ cannot be entered. The size of the set Θ will be denoted by $|\Theta|$. The stochastic process $(\bar{N}, F)$ is a stationary Markov process of which each component N_j , $j=1, \dots, s$, has a

birth-death structure. This means that the time until a transition occurs from a state $(\bar{n}, \varphi)$ to some other state is negative exponentially distributed, and that one-step transitions are only possible to states with at most one unit more or one unit less in one of the first s entries. The one-step transition rates are defined to be: for $(\bar{n}, \varphi) \in \mathbb{N}^s \times \Theta$, $\psi \in \Theta$, $j=1, \dots, s$,

$\chi a_j(\bar{n}, \varphi, \psi)$: the arrival rate to queue j at state $(\bar{n}, \varphi)$, leading to a transition to the state $(\bar{n} + \bar{e}_j, \psi)$;
 $d_j(\bar{n}, \varphi, \psi)$: the departure rate from queue j at state $(\bar{n}, \varphi)$, leading to a transition to the state $(\bar{n} - \bar{e}_j, \psi)$, with $d_j(\bar{n}, \varphi, \psi) = 0$ if $n_j = 0$;
 $u(\bar{n}, \varphi, \psi)$: the phase-transition rate from state $(\bar{n}, \varphi)$ to state $(\bar{n}, \psi)$;

here, $\bar{e}_j \in \mathbb{N}^s$ is the vector with zero entries except an entry of one at the j^{th} position ($j=1, \dots, s$), and χ is a parameter which will be used as variable in power-series expansions; the relative arrival rates $a_j(\bar{n}, \varphi, \psi)$ are assumed to be normalized such that the systems are stable for $\chi < 1$.

2.2. Balance equations

The state probabilities are defined as follows: for $(\bar{n}, \varphi) \in \mathbb{N}^s \times \Theta$,

$$p(\bar{n}, \varphi) := \Pr\{(\bar{N}, F) = (\bar{n}, \varphi)\}. \quad (2.1)$$

The description of the process in the previous section implies that the state probabilities (2.1) satisfy the following balance equations, for $(\bar{n}, \varphi) \in \mathbb{N}^s \times \Theta$,

$$\begin{aligned} & \left[\sum_{j=1}^s \sum_{\psi \in \Theta} \left[\chi a_j(\bar{n}, \varphi, \psi) + d_j(\bar{n}, \varphi, \psi) \right] + \sum_{\psi \in \Theta} u(\bar{n}, \varphi, \psi) \right] p(\bar{n}, \varphi) = \\ & = \chi \sum_{j=1}^s \sum_{\psi \in \Theta} a_j(\bar{n} - \bar{e}_j, \psi, \varphi) p(\bar{n} - \bar{e}_j, \psi) I\{n_j > 0\} \\ & + \sum_{j=1}^s \sum_{\psi \in \Theta} d_j(\bar{n} + \bar{e}_j, \psi, \varphi) p(\bar{n} + \bar{e}_j, \psi) + \sum_{\psi \in \Theta} u(\bar{n}, \psi, \varphi) p(\bar{n}, \psi); \end{aligned} \quad (2.2)$$

here, $I\{E\}$ stands for the indicator function of the event E . The infinite set of linear equations (2.2) can not be solved recursively, in general,

because the equation for $p(\bar{n}, \varphi)$, $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$, involves terms with $p(\bar{n} + \bar{e}_j, \psi)$, $j=1, \dots, s$, $\psi \in \Theta$, and because there exist no local balance relations for most models in the class of models that will be considered.

2.3. Conditions for application of the algorithm

The solution method for the set of equations (2.2) on which the standard p.s.a. is based relies on the following property of the state probabilities:

$$p(\bar{n}, \varphi) = O(x^{n_1 + \dots + n_s}), \quad \text{as } x \downarrow 0, \quad \text{for } (\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta. \quad (2.3)$$

This property can be shown to hold on the following conditions: for each state $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$, $\bar{n} \neq \bar{0}$, either $p(\bar{n}, \varphi) = 0$ (the state cannot be entered), or there exists a path $\vartheta_0, \vartheta_1, \dots, \vartheta_\kappa$ in Θ for some $\kappa \geq 0$ such that $\vartheta_0 = \varphi$, $u(\bar{n}, \vartheta_{i-1}, \vartheta_i) > 0$ for $i=1, \dots, \kappa$, and

$$\sum_{j=1}^s \sum_{\psi \in \Theta} d_j(\bar{n}, \vartheta_\kappa, \psi) > 0; \quad (2.4)$$

i.e., for each reachable $\bar{n}$, $\bar{n} \neq \bar{0}$, there must be at least one positive departure rate, and for each reachable state $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$, $\bar{n} \neq \bar{0}$, the probability that a departure occurs before any arrival takes place, after the process has entered this state, must be positive. The proof of this assertion is technical, and it is therefore omitted here. The above condition is fulfilled for the polling systems which are usually considered for modeling computer-communication systems, but it is not, for instance, if serving only starts when the number of jobs in a system has reached some threshold larger than 1. A stronger condition than the one above, for which it is easier to verify that (2.3) holds, cf. Blanc [3], is the condition that for each reachable state $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$, $\bar{n} \neq \bar{0}$, there is at least one positive departure rate (i.e., $\kappa=0$ in (2.4) for each φ), but this condition does not hold in polling systems for states in which the server is switching. It will be clear that (2.4) cannot hold for empty states $(\bar{0}, \varphi)$, $\varphi \in \Theta$. For these specific states, property (2.3) trivially holds. However, these states require a special treatment, as will be seen in the next section.

2.4. The computation scheme

The computation scheme of the p.s.a. for the class of models described in section 2.1 will be given here in its simplest form. A more complicated form may be needed in order to avoid numerical instabilities. These matters will be discussed in the next section. Based on property (2.3) the following power-series expansions are introduced: for $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$,

$$p(\bar{n}, \varphi) = x^{n_1 + \dots + n_S} \sum_{k=0}^{\infty} x^k b(k; \bar{n}, \varphi), \quad (2.5)$$

When the power-series (2.5) have been substituted into the balance equations (2.2), then equating the coefficients of corresponding powers of x in the resulting equations leads to the following set of equations for computing the coefficients of the power-series (2.5): for $(\bar{n}, \varphi) \in \mathbb{N}^S \times \Theta$, for $k=0, 1, 2, \dots$,

$$\begin{aligned} & \left\{ \sum_{\psi \in \Theta} \left[u(\bar{n}, \varphi, \psi) + \sum_{j=1}^S d_j(\bar{n}, \varphi, \psi) \right] \right\} b(k; \bar{n}, \varphi) = \sum_{\psi \in \Theta} u(\bar{n}, \psi, \varphi) b(k; \bar{n}, \psi) + \\ & + \sum_{j=1}^S \sum_{\psi \in \Theta} \left[a_j(\bar{n} - \bar{e}_j, \psi, \varphi) b(k; \bar{n} - \bar{e}_j, \psi) I\{n_j > 0\} \right. \\ & \quad \left. - a_j(\bar{n}, \varphi, \psi) b(k-1; \bar{n}, \varphi) I\{k > 0\} \right] \\ & + \sum_{j=1}^S \sum_{\psi \in \Theta} d_j(\bar{n} + \bar{e}_j, \psi, \varphi) b(k-1; \bar{n} + \bar{e}_j, \psi) I\{k > 0\}. \end{aligned} \quad (2.6)$$

This set of equations (2.6) forms a recursive scheme with respect to the components $(k; \bar{n})$. In order to make this observation more precise we introduce the following partial ordering $\prec$ of vectors $(i; \bar{m}, \psi), (k; \bar{n}, \varphi) \in \mathbb{N}^{1+S} \times \Theta$:

$$\begin{aligned} (i; \bar{m}, \psi) \prec (k; \bar{n}, \varphi) \quad & \text{if } i + m_1 + \dots + m_S < k + n_1 + \dots + n_S; \\ & \text{or if } i + m_1 + \dots + m_S = k + n_1 + \dots + n_S \text{ and } i < k. \end{aligned} \quad (2.7)$$

It is readily verified that the set of equations (2.6) expresses coefficients $b(k; \bar{n}, \varphi)$ in terms of coefficients with a lower order with respect to $\prec$ with the exception of the terms with $b(k; \bar{n}, \psi)$, $\psi \in \Theta$. Hence, the set of equations (2.6) can be divided into subsets of at most $|\Theta|$ equations with unknowns $b(k; \bar{n}, \varphi)$, $\varphi \in \Theta$. The same conditions which guarantee that

(2.3) holds, cf. (2.4), also guarantee that these subsets of equations possess a unique solution. The only exceptions form the empty states, i.e. states with $\bar{n} = \bar{0}$, for which all departure rates vanish so that the equations (2.6) reduce to: for $\varphi \in \Theta$, for $k=0,1,2,\dots$,

$$\begin{aligned} \sum_{\psi \in \Theta} u(\bar{0}, \varphi, \psi) b(k; \bar{0}, \varphi) = & - \sum_{j=1}^S \sum_{\psi \in \Theta} a_j(\bar{0}, \varphi, \psi) b(k-1; \bar{0}, \varphi) I\{k>0\} \\ & + \sum_{j=1}^S \sum_{\psi \in \Theta} d_j(\bar{e}_j, \varphi, \varphi) b(k-1; \bar{e}_j, \varphi) I\{k>0\} + \sum_{\psi \in \Theta} u(\bar{0}, \varphi, \psi) b(k; \bar{0}, \psi). \end{aligned} \quad (2.8)$$

It is readily verified by summing the equations (2.8) over φ , $\varphi \in \Theta$, that these are dependent sets of equations for the coefficients $b(k; \bar{0}, \varphi)$, $\varphi \in \Theta$, for each k , $k=0,1,\dots$. To this end, it should be noted that for each k , $k=0,1,\dots$,

$$\sum_{\varphi \in \Theta} b(k; \bar{0}, \varphi) \sum_{j=1}^S \sum_{\psi \in \Theta} a_j(\bar{0}, \varphi, \psi) = \sum_{j=1}^S \sum_{\psi \in \Theta} b(k; \bar{e}_j, \psi) \sum_{\varphi \in \Theta} d_j(\bar{e}_j, \varphi, \varphi),$$

because of a necessary balance in transitions between the set of empty states and the set of states with one job in the system. In order to obtain an additional equation the law of total probability can be used. Substituting (2.5) into the law of total probability gives:

$$\sum_{\varphi \in \Theta} b(0; \bar{0}, \varphi) = 1, \quad (2.9)$$

$$\sum_{\varphi \in \Theta} b(k; \bar{0}, \varphi) = - \sum_{0 < n_1 + \dots + n_s \leq k} \sum_{\psi \in \Theta} b(k - n_1 - \dots - n_s; \bar{n}, \psi), \quad k=1,2,\dots$$

Note that the right hand sides of (2.9) contain coefficients of states of a lower order with respect to $\prec$ than $(k; \bar{0}, \varphi)$. Now, all but one of the equations (2.8) together with (2.9) determine $b(k; \bar{0}, \varphi)$, $\varphi \in \Theta$, for $k=0,1,\dots$, if the Markov process $(\bar{N}, F)$, conditioned to the event that $\bar{N} = \bar{0}$ and no arrivals occur, is an irreducible Markov process on a subset of Θ (note that the determinants of these sets of equations do not depend on k , $k=0,1,\dots$, so that it is sufficient to consider the solvability of the set of equations for $k=0$).

The p.s.a. is most efficient when the coefficients $b(k; \bar{n}, \varphi)$ can be computed recursively from (2.6) and (2.9). Whether this is possible depends on the structure of the supplementary space. The computation scheme is recursive if for each $\bar{n} \in \mathbb{N}^S$ the values of the supplementary variable F can be ordered such that transitions without $\bar{N}$ leaving the state $\bar{n}$ are only possible in one direction. More formally, if $\prec_{\bar{n}}$ is an ordering of the set Θ , then it should hold that

$$u(\bar{n}, \varphi, \psi) = 0, \quad \text{if } \psi \prec_{\bar{n}} \varphi, \quad \text{for all } \varphi, \psi \in \Theta. \quad (2.10)$$

The ordering does not need to be the same for all $\bar{n} \in \mathbb{N}^S$. If no ordering with the property (2.10) exists for some $\bar{n}$, then a set of at most $|\Theta|$ linear equations has to be solved for such an $\bar{n}$. Therefore, Coxian distributions are much easier to handle with the p.s.a than more general phase-type distributions.

Once the coefficients of the power-series expansions of the state probabilities have been determined, those of the moments of the joint queue length distribution can be obtained as well. Write

$$E\left\{\prod_{j=1}^S N_j^{\nu_j}\right\} = \sum_{k=0}^{\infty} x^k f(k; \bar{\nu}), \quad \bar{\nu} \in \mathbb{N}^S. \quad (2.11)$$

It follows from (2.11) and (2.5) that for $\bar{\nu} \in \mathbb{N}^S$, $k=0,1,2,\dots$,

$$f(k; \bar{\nu}) = \sum_{0 \leq n_1 + \dots + n_S \leq k} \dots \sum_{\varphi \in \Theta} \prod_{j=1}^S n_j^{\nu_j} b(k - n_1 - \dots - n_S; \bar{n}, \varphi). \quad (2.12)$$

It is more convenient for obtaining moments of the queue length distribution to compute first their coefficients via (2.12) and then to use (2.11) than to compute first the state probabilities via (2.5) and then the moments directly from the state probabilities. In the first way algorithms for accelerating the convergence can be applied to partial sums of the series (2.11), and the storage requirement for the coefficients can be reduced; see sections 2.5 and 2.6.

2.5. Convergence of the power-series

Experience has learned that the power-series (2.5) and (2.11) usually do not converge for all values of x for which a system is stable (by definition for $x < 1$). One way to overcome this difficulty is to introduce the following bilinear mapping of the interval $[0,1]$ onto itself,

$$\vartheta = \frac{(1+G)x}{1+Gx}, \quad G \geq 0. \quad (2.13)$$

This transformation maps possible singularities of the power series in the region

$$\left| x - \frac{G}{1+2G} \right| > \frac{1+G}{1+2G}, \quad |x| \leq 1. \quad (2.14)$$

outside the unit circle in the complex ϑ -plane. Another computation scheme is then obtained by introducing power-series expansions of the state probabilities as functions of ϑ , by replacing x by ϑ in the balance equations (2.2) according to (2.13), and by substituting the power-series in ϑ into these equations. Equating coefficients of corresponding powers of ϑ in the resulting equations leads to a set of equations, which differ from (2.6) mainly through the occurrence of terms with coefficients of the form $b(k-2; \bar{n} + \bar{e}_j, \psi)$. Any singularity outside the circle $|x - \frac{1}{2}| = \frac{1}{2}$ may be removed from the unit disk by this procedure with an appropriate choice of the parameter G .

Another technique for removing singularities from inside the unit disk is application of the epsilon algorithm or a related algorithm. The epsilon algorithm aims to accelerate the convergence of slowly convergent sequences or to determine a value for divergent sequences, cf. Wynn [25], Brezinski [12]. It converts a polynomial into a quotient of two polynomials. The epsilon algorithm consists of the following triangular recursive scheme: for $m=0,1,\dots$, $\kappa=0,1,\dots$,

$$\epsilon_{\kappa+1}^{(m)} = \epsilon_{\kappa-1}^{(m+1)} + [\epsilon_{\kappa}^{(m+1)} - \epsilon_{\kappa}^{(m)}]^{-1}, \quad \epsilon_{-1}^{(m)} = 0, \quad \epsilon_0^{(m)} = S_m; \quad (2.15)$$

here, the initial sequence S_m , $m=0,1,\dots$, consists of partial sums of a series. Only the even sequences $\{\epsilon_{2\kappa}^{(m)}, m=0,1,\dots\}$, $\kappa=1,2,\dots$, may be sequences which converge faster to a limit than the initial sequence. The

odd sequences are only intermediate steps in the calculation scheme. When S_m is the partial sum of a power-series, say

$$S_m = S_m(x) = \sum_{k=0}^m c_k x^k, \quad m = 0, 1, \dots, \quad (2.16)$$

then the epsilon algorithm transforms this sequence of polynomials into sequences of quotients of two polynomials. More precisely, $\epsilon_{2k}^{(m-2k)}$ will be a quotient of a polynomial of degree $m-k$ over a polynomial of degree k , and for $m=2k, 2k+1, \dots$,

$$\left| S_m - \epsilon_{2k}^{(m-2k)} \right| = O(x^{m+1}), \quad x \rightarrow 0, \quad k = 1, 2, \dots, \quad (2.17)$$

see Wynn [25]. When the heavy traffic behaviour of the moments of the queue length distribution is known beforehand, the performance of the epsilon algorithm can be improved by a modification of the initial values $\epsilon_0^{(m)}$, cf. Blanc [5]. Before application of the epsilon algorithm the coefficients of the power-series are extrapolated to take into account the pole at $x = 1$. It means that we take for first order poles

$$\epsilon_0^{(m)} = S_m + c_m \frac{x^{m+1}}{1-x}, \quad m = 1, 2, \dots, \quad (2.18)$$

and for second order poles

$$\epsilon_0^{(m)} = S_m + \left[c_m + \frac{c_m - c_{m-1}}{1-x} \right] \frac{x^{m+1}}{1-x}, \quad m = 1, 2, \dots, \quad (2.19)$$

instead of the last relation of (2.15); here S_m is of the form (2.16) and the c_k , $k=1, 2, \dots$, stand for coefficients of a series as defined in (2.11). The pole at $x = 1$ is preserved in other (even) sequences produced by the epsilon algorithm. It should be noted that not every queue grows without bound as $x \uparrow 1$ in some systems (see, e.g., the discussion in section 4.5); modifications (2.18) and (2.19) should only be applied to those moments which do have a pole at $x = 1$ in order to accelerate the convergence, although $\epsilon_0^{(m)}$ defined by (2.18) respectively (2.19) will converge to the same limit as S_m if the latter sequence is convergent.

The epsilon algorithm turns a divergent series into a convergent series if the analytic continuation of the function defined by the series at $x = 0$ possesses only a finite number of poles as singularities inside the unit circle $|x| \leq 1$. The latter seems to hold for all models considered. However, it may happen that the power series are so strongly divergent that numerical instabilities occur when a large number of terms is computed. In that case, a conformal mapping as discussed above, cf. (2.13), should be used together with the epsilon algorithm.

The value of G in the mapping (2.13), the number of terms M of the power-series expansions, and the number of steps κ in the epsilon algorithm, cf. (2.15), which are needed to reach a certain accuracy, depend on various properties of the models. Generally, these quantities increase with increasing load, with increasing number of queues, and with increasing asymmetry between the parameters of the various queues. Numerical experience has learned that application of the epsilon algorithm strongly improves the performance of the p.s.a. and that, in many cases, it even leads to good estimations of heavy traffic limits.

2.6. On the implementation of the algorithm

For most models, limitations on storage capacity are more important restrictions on the applicability of the p.s.a. than limitations on computing time. The complexity of the p.s.a. mainly depends on the number of stations s and on the size of the supplementary space Θ . The evaluation of power-series expansions up to the M^{th} power of x requires the computation of

$$\binom{M+s+1}{s+1} |\Theta| \quad (2.20)$$

coefficients $b(k; \bar{n}, \varphi)$, namely those with $k+n_1+\dots+n_s \leq M$, $\varphi \in \Theta$. The complexity of the computation of a single coefficient $b(k; \bar{n}, \varphi)$ depends on the structure of the model, in particular on the number of non-zero transition rates. In order to make an efficient use of the available memory space we map the multi-dimensional region of lattice points $k+n_1+\dots+n_s \leq M$ onto the set of integers by means of the one-to-one mapping, cf. Blanc [5],

$$C(k; \bar{n}) = \sum_{j=0}^s \binom{k+j+\sum_{i=1}^j n_i}{j+1}. \quad (2.21)$$

This procedure enlarges the number of terms of the power-series expansions which can be computed with a given storage capacity at the costs of increased computation time needed for the determination of the location of the coefficients in the array in which they are stored. A further reduction of storage requirement can be realized when only a limited number of performance measures have to be evaluated. In most cases, one is not interested in all individual state probabilities. Then, the coefficients of the power-series expansions of the important performance measures can be aggregated during the execution of the p.s.a., cf., e.g., (2.12), and stored in separate (relatively small) arrays, while the coefficients of the state probabilities can be deleted as soon as they are not needed anymore in further computations. This approach reduces storage requirement for calculating M terms of the power-series expansions to $D_M \times |\Theta|$, where D_M is the largest distance (in terms of the mapping $C(k; \bar{n})$, cf. (2.21)) between coefficients occurring in a single equation of (2.6), cf. Blanc [5],

$$D_M = \binom{M+s}{s}, \quad \text{if } G = 0; \quad D_M = \binom{M+s}{s} + \binom{M+s-2}{s-1}, \quad \text{if } G > 0. \quad (2.22)$$

3. Polling systems

Models for polling systems usually consist of several stations (queues), each with an arrival stream of jobs, which are attended to by a single server. The server visits the stations according to some control rule (service discipline). In many cases, switch-over times or set-up times are required when the server changes service from one queue to another. Important areas for application of these models are computer-communication systems, in which several stations share a common communication channel and compete for access to this channel, and manufacturing systems, in which several types of products have to be manufactured on a single production unit.

3.1. Service disciplines

The service disciplines for polling systems can often be divided into three parts, which can be chosen independently of each other:

- A. a rule for the order in which the server visits the queues;
- B. rules for the number of services per visit to the various queues;
- C. a rule for the behaviour of the server when the system is empty.

Examples of order-of-visit rules are:

- A1. polling in a fixed periodic order (cyclic: 1,2,...,s, star: 1,2,1,3,...,1,s, scanning: 1,2,...,s,s,s-1,...,1, or according to some general polling table);
- A2. random or Markovian polling: the next queue to be visited is determined by a random mechanism which may depend on the current position of the server (Markovian polling) or not (random polling), cf. Boxma & Weststrate [11];
- A3. polling according to fixed priorities attributed to the queues;
- A4. polling according to a dynamic (state-dependent) rule such as priority for the longest queue, cf., e.g., Cohen [14].

The choice of the order-of-visit rule will depend on the availability of information about the presence of jobs at the various stations. The rules A1 and A2 require only local information, about the station where the server is present, but the rules A3 and A4 require also information from other stations. Further, this choice may depend on the configuration of the system, i.e., on the existence or non-existence of a direct connection between pairs of stations in the network, and on the distances between the stations, in terms of mean switching times.

Examples of number-of-services rules are:

- B1. exhaustive service (the server remains serving until a queue becomes empty);
- B2. gated service (all jobs present in a queue at the instant at which the server arrived at that queue are served);
- B3. limited service (a fixed number of jobs is served, at most);
- B4. Bernoulli service (after each service another service may be started with a fixed probability, cf. Servi [21], Tediato [24]);
- B5. semi-exhaustive service (the server attends to a queue until the number of jobs in that queue has become one less than the number of jobs in that queue at the instant at which the server arrived at that queue, cf. Cohen [13]).

The number-of-services rules may be different for the various queues, and even may be different at various visits to the same queue (e.g., when a queue occurs more than once on a polling table).

Examples of empty-system rules are:

- C1. the server keeps on switching according to the order-of-visit rule;
- C2. the server remains at the last served queue;

- C3. the server goes to a state of rest;
 C4. the server goes to a specific queue (e.g., the queue with the highest load, or the queue with the largest arrival rate).

The choice of the empty-system rule will also depend on the availability of information. Rule C1 requires only local information, in fact, the server does not even have to know that the system is empty. The other rules require information from all stations.

As far as the choices of these rules are not limited by the physical configuration of a system or by the available information, they can be used to optimize the performance of a system with respect to some criterium.

3.2. Complexity of the algorithm

The complexity of the p.s.a. for polling systems is given by (2.20), where the size of the supplementary space Θ depends on the service discipline and on the number of phases of the interarrival, service and switching time distributions. Here, the discussion will be confined to Poisson arrival streams at each station. Let Ψ_j^1 be the number of phases of the distribution of the service times at queue j , $j=1, \dots, s$, and $\Psi_{i,j}^0$ the number of phases of the distribution of the switching times from queue i to queue j , $i, j=1, \dots, s$. First, consider polling in a fixed (static) periodic order. Such order-of-visit rules can generally be described by a polling table of some finite length L , $L \geq s$. A polling table can be constructed by a mapping $\ell : \{1, \dots, L\} \rightarrow \{1, \dots, s\}$. If the number-of-services rules is limited service for each visit, with limit K_h for the h^{th} entry on the table, $h=1, \dots, L$, then the size of the supplementary space has to be

$$|\Theta| = \sum_{h=1}^L [K_h \Psi_{\ell(h)}^1 + \Psi_{\ell(h-1), \ell(h)}^0] \geq 2L \geq 2s. \quad (3.1)$$

The lower bound $2L$ is realized when all service times and switching times are exponentially distributed and all service limits are equal to 1, and the lower bound $2s$ is realized when moreover the polling order is cyclic. Next, consider order-of-visit rules which require only information on the current position of the server and on the number of jobs at the stations to determine the next station to be visited. This set of rules includes Markovian polling, polling with fixed priorities, and polling with priority for the longest queue. If the number-of-services rules is limited

service for each visit, with limit K_j for queue j , $j=1, \dots, s$, then the size of the supplementary space has to be

$$|\Theta| = \sum_{j=1}^s K_j \Psi_j^1 + \sum_{i=1}^s \sum_{j=1}^s \Psi_{i,j}^0 \geq s + s(s-1) = s^2. \quad (3.2)$$

The lower bound s^2 is realized when all service times and switching times are exponentially distributed (while we assumed that $\Psi_{i,i}^0=0$, $i=1, \dots, s$) and all service limits are equal to 1. This lower bound presumes that switches of the server may occur between each pair of stations. The latter does not necessarily hold for Markovian polling; for this discipline the lower bound is equal to the number of non-zero entries in the matrix of transition probabilities for the server. When the distributions of the switching times only depend on the station to which (and not on the station from which) the server is moving, then $\Psi_{i,j}^0 = \Psi_j^0$, $i, j=1, \dots, s$, and the size of the supplementary space can be reduced to:

$$|\Theta| = \sum_{j=1}^s K_j \Psi_j^1 + \sum_{j=1}^s \Psi_j^0 \geq 2s. \quad (3.3)$$

When switching times may be neglected, the size of the required supplementary space can be found by taking $\Psi_{i,j}^0=0$, $i, j=1, \dots, s$, in (3.1), (3.2), (3.3), where the lower bounds then reduce to s . The contribution to the size of the supplementary space of a station with a Bernoulli schedule (including exhaustive service) is the same as that of a station with 1-limited service. Therefore, systems with Bernoulli schedules are most suitable for application of the p.s.a.. Stations with gated or semi-exhaustive service discipline require, in principle, an unbounded supplementary space, and would therefore not fit in the framework of the class of models described in section 2.1. However, only a finite number of terms (M) of the power-series expansions are computed in practice, which implies that states with more than M jobs in the system are not considered. Consequently, the size of the supplementary space can still be derived from (3.1), (3.2), (3.3) for the various order-of-visit rules when there are stations with gated or semi-exhaustive service, namely by taking M as the service limit for these stations. But it will be clear that the p.s.a. is not very suitable for the analysis of systems with gated-type service dis-

ciplines. The foregoing argument also implies that it is useless to consider service limits larger than M when using the p.s.a., because performance measures for queues with such limits will be the same as when they had been computed with the exhaustive service discipline at those queues. In fact, the queue length process at stations with a limited service discipline is very similar to that at equivalent stations with exhaustive service in light traffic, while the range of the load for which this similarity continues increases with the service limit. This similarity to equivalent stations with exhaustive service is much weaker for stations with Bernoulli schedules than for stations with as limit the mean number of services which is possible with the Bernoulli schedules (i.e., with $K_j = 1/(1-q_j)$, where q_j is the probability that a next job may be served at the same station), cf. the numerical examples in Blanc [7]. As a consequence, systems with Bernoulli schedules are much more easily studied over all parameter values of the service discipline than systems with limited service, at least with the aid of the p.s.a.. Another advantage of Bernoulli schedules over limited service may be, especially in optimization problems, that they consist of continuous parameters. A disadvantage of Bernoulli schedules may be their random nature.

The foregoing discussion of the complexity of the p.s.a. only refers to order-of-visit rules and number-of-services rules, and ignores the influence of empty-system rules. In fact, the above observations hold if the behaviour of the server when the system is empty is similar to that when the system is not empty, e.g., for rule C1 and possibly for rule C4, depending on how interruptions of switches when the system is empty and a job arrives are handled. When this behaviour is deviating then the size of the supplementary space may have to be larger than indicated above. For instance, when rule C3 is applied and if $\psi_{0,j}^0$ is the number of phases of the distribution of the switching times from the state of rest to queue j , $j=1, \dots, s$, while switches to the state of rest are instantaneous, then (3.2) should be modified to

$$|\Theta| = \sum_{j=1}^s K_j \psi_j^1 + \sum_{i=0}^s \sum_{j=1}^s \psi_{i,j}^0 \geq s + s^2. \quad (3.4)$$

while (3.3) remains unchanged if, moreover, $\psi_{0,j}^0 = \psi_j^0$, $j=1, \dots, s$. Finally, we note that the process $(\bar{N}, F)$ restricted to $\bar{N} = \bar{0}$ is not an irreducible

Markov process in the case of rule C2 (each reachable empty state forms an irreducible subchain in this case), so that this rule does not fit in the framework of section 2.4.

4. Systems with a polling table and Bernoulli schedules

In this section the p.s.a. will be discussed in more detail for the class of polling models with infinite buffers, with Poisson arrival streams, with Coxian service and switching time distributions, with a fixed periodic visit order, and with a Bernoulli schedule for each visit. Section 5 contains some remarks on extensions of this class of models.

4.1. Description of the model

The system consists of s queues and a single server. Jobs arrive at queue j according to a Poisson process with rate λ_j , $j = 1, \dots, s$. Each queue may contain an unbounded number of jobs. The server inspects the queues in an order which is determined by a polling table of finite length L . This table will be described by a mapping $\ell : \{1, \dots, L\} \rightarrow \{1, \dots, s\}$. Throughout, it will be assumed that each station occurs at least once on the table, and that L has been chosen as small as possible, given a fixed visit order. Further, the convention $\ell(0) = \ell(L)$ will be needed and used. Bernoulli schedules will be used to determine the number of service during the visits of the server to the stations. When the server arrives at a queue, at least one job is served, unless this queue is empty (in which case the server directly proceeds to the next queue on the polling table). After the completion of a service at queue $\ell(h)$ the server starts serving another job at this queue with probability q_h if queue $\ell(h)$ has not yet been emptied; otherwise the server proceeds to the next queue on the polling table ($h=1, \dots, L$). At each station jobs are served in order of arrival. Service times of jobs arriving at queue j are assumed to be distributed according to a Coxian distribution with ν^{th} moment $\gamma_{\nu j}$, $\nu=1, 2, \dots$, $j=1, \dots, s$. The Coxian service time distribution at station j , $j=1, \dots, s$, consists of ψ_j^1 phases; with probability $\pi_j^{1, \varphi}$, a service is composed of phases $\varphi, \varphi-1, \dots, 1$, $\varphi=1, \dots, \psi_j^1$, and the transition rate from phase φ is $\mu_j^{1, \varphi}$, $\varphi=1, \dots, \psi_j^1$. Consequently, the Laplace-Stieltjes transform of the service time distribution at station j , $j=1, \dots, s$, is given by

$$\gamma_j(\omega) = \sum_{\varphi=1}^{\Psi_j^1} \pi_j^{1,\varphi} \prod_{\psi=\varphi}^{\Psi_j^1} \frac{\mu_j^{1,\psi}}{\mu_j^{1,\psi} + \omega}, \quad \operatorname{Re} \omega \geq 0. \quad (4.1)$$

The times which are needed for switching from queue $\ell(h-1)$ to queue $\ell(h)$ are also assumed to be distributed according to a Coxian distribution, with ν^{th} moment $\delta_{\nu h}$, $\nu=1,2,\dots$, and with parameters Ψ_h^0 , $\pi_h^{0,\varphi}$, $\mu_h^{0,\varphi}$, $\varphi=1,\dots,\Psi_h^0$, which are defined in a similar way as those of the service time distributions, $h=1,\dots,L$.

The sum of the arrival processes at the various queues is a Poisson process with rate $\wedge := \sum_{j=1}^s \lambda_j$. The mean service time of an arbitrary job is γ_{1j} with probability $\lambda_j/\wedge$, $j=1,\dots,s$. Hence, the first two moments β_1 and β_2 of the distribution of the service time of an arbitrary job are given by:

$$\beta_1 = \sum_{j=1}^s \frac{\lambda_j}{\wedge} \gamma_{1j}, \quad \beta_2 = \sum_{j=1}^s \frac{\lambda_j}{\wedge} \gamma_{2j}. \quad (4.2)$$

The offered load ρ_j to station j and the offered load ρ to the system are defined by

$$\rho_j := \lambda_j \gamma_{1j}, \quad \rho := \sum_{j=1}^s \rho_j = \wedge \beta_1. \quad (4.3)$$

The first two moments σ_1 and σ_2 of the total switching time during one cycle of the server along the queues according to the polling table are given by:

$$\sigma_1 = \sum_{h=1}^L \delta_{1h}, \quad \sigma_2 = \sum_{h=1}^L \delta_{2h} + 2 \sum_{h=1}^L \sum_{i=1}^{h-1} \delta_{1h} \delta_{1i}. \quad (4.4)$$

4.2. Conditions for stability

Kühn [19] has derived general conditions for stability of cyclic polling systems. Similar ideas lead for the present model with Bernoulli schedules and a general periodic polling order to the following conditions:

$$\lambda_j E\{C\} < m_j, \quad \text{for } j = 1, \dots, s; \quad (4.5)$$

here, $E\{C\}$ stands for the mean cycle time of the server, i.e. the mean time the server needs to go once along the queues in the order listed on the polling table, so that $\lambda_j E\{C\}$ is the mean number of jobs which arrive at queue j during one cycle, and m_j stands for the mean number of jobs at queue j which can be served during one cycle, $j=1, \dots, s$. The latter quantities depend on the polling table and on the Bernoulli parameters, and are readily verified to be equal to:

$$m_j = \sum_{h=1}^L \frac{I\{\ell(h)=j\}}{1 - q_h}, \quad j = 1, \dots, s. \quad (4.6)$$

Here, $m_j := \infty$ whenever there is at least one h , $h=1, \dots, L$, with $\ell(h)=j$ and $q_h=1$. The mean cycle time can be found by noting that, with V_h , $h=1, \dots, L$, the duration of the h^{th} visit in a cycle (to queue $\ell(h)$):

$$E\{C\} = \sigma_1 + \sum_{h=1}^L E\{V_h\}, \quad (4.7)$$

and, by balance arguments for the flows of jobs into and out of the s queues,

$$\lambda_j E\{C\} = \sum_{h=1}^L I\{\ell(h)=j\} E\{V_h\} / \delta_{1j}, \quad j = 1, \dots, s. \quad (4.8)$$

Eliminating $E\{V_h\}$, $h=1, \dots, L$, from (4.7) with (4.8) readily leads to

$$E\{C\} = \frac{\sigma_1}{1 - \rho}. \quad (4.9)$$

The conditions (4.5) can be summarized in the following condition:

$$x := \rho + \sigma_1 \max_{j=1, \dots, s} \{\lambda_j / m_j\} < 1. \quad (4.10)$$

This condition depends on the service discipline (in this case, the polling table and the Bernoulli schedules). An intrinsic condition for stability of a polling system is $\rho < 1$. If this condition is satisfied then it is possible to choose a service discipline such that the system is stable,

e.g., one with exhaustive service at each station. We will call x the occupancy of the system. Because this quantity x will be used as variable in power-series expansions, the arrival rates will be written, cf. section 2.1, as

$$\lambda_j = a_j x, \quad j = 1, \dots, s. \quad (4.11)$$

4.3. Balance equations

For the formulation of the balance equations for the class of polling systems described in section 4.1 it is most appropriate to introduce a triple (H, Z, Φ) of supplementary variables in order to transform the queue length process into a Markov process. The variable H will indicate the actual position on the polling table (the value of H , in the range $1, \dots, L$, changes at instants at which the server leaves a station), the variable Z will indicate whether the server is switching ($Z=0$) or serving ($Z=1$), and the variable Φ will indicate the actual phase of either the switching time or the service time. The state probabilities are defined as follows: for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\zeta=0, 1$, $\varphi=1, \dots, \Psi_h^0$ if $\zeta=0$, $\varphi=1, \dots, \Psi_{\ell(h)}^1$ if $\zeta=1$,

$$p(\bar{n}, h, \zeta, \varphi) := \Pr\{(\bar{N}, H, Z, \Phi) = (\bar{n}, h, \zeta, \varphi)\}. \quad (4.12)$$

Noting that the Coxian distributions have been defined such that completion of a service or a switch can only occur if $\Phi=1$, cf. section 4.1, the balance equations for the state probabilities (4.12) are readily verified to be, for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$,

$$\begin{aligned} \left[x \sum_{j=1}^s a_j + \mu_h^{0, \varphi} \right] p(\bar{n}, h, 0, \varphi) &= x \sum_{j=1}^s a_j p(\bar{n} - \bar{e}_j, h, 0, \varphi) I\{n_j > 0\} \\ &+ \mu_h^{0, \varphi+1} p(\bar{n}, h, 0, \varphi+1) I\{\varphi < \Psi_h^0\} + \mu_{h-1}^{0, 1} \pi_h^{0, \varphi} p(\bar{n}, h-1, 0, 1) I\{n_{\ell(h-1)} = 0\} \\ &+ \mu_{\ell(h-1)}^{1, 1} \pi_h^{0, \varphi} p(\bar{n} + \bar{e}_{\ell(h-1)}, h-1, 1, 1) \left[1 - q_{h-1} I\{n_{\ell(h-1)} > 0\} \right]; \quad (4.13) \end{aligned}$$

and for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_{\ell(h)}^1$, $n_{\ell(h)} > 0$,

$$\begin{aligned}
\left[\times \sum_{j=1}^S a_j + \mu_{\ell(h)}^{1,\varphi} \right] p(\bar{n}, h, 1, \varphi) &= \times \sum_{j=1}^S a_j p(\bar{n} - \bar{e}_j, h, 1, \varphi) I\{n_j > 0\} \\
&+ \mu_{\ell(h)}^{1,\varphi+1} p(\bar{n}, h, 1, \varphi+1) I\{\varphi < \Psi_{\ell(h)}^1\} + \mu_h^{0,1} \pi_{\ell(h)}^{1,\varphi} p(\bar{n}, h, 0, 1) \\
&+ q_h \mu_{\ell(h)}^{1,1} \pi_{\ell(h)}^{1,\varphi} p(\bar{n} + \bar{e}_{\ell(h)}, h, 1, 1). \quad (4.14)
\end{aligned}$$

It should be noted that for all φ , $\varphi=1, \dots, \Psi_{\ell(h)}^1$,

$$p(\bar{n}, h, 1, \varphi) = 0, \quad \text{if } n_{\ell(h)} = 0, \quad h = 1, \dots, L. \quad (4.15)$$

4.4. The computation scheme

First, it will be shown that the Markov process $(\bar{N}, H, Z, \Phi)$ satisfies conditions (2.4), and, hence, that the state probabilities (4.12) possess the light traffic behaviour as indicated in (2.3). For this purpose we introduce for each $\bar{n} \in \mathbb{N}^S$, $\bar{n} \neq \bar{0}$, an ordering $\prec_{\bar{n}}$ of the vectors of supplementary values (h, ξ, φ) . For each $\bar{n} \in \mathbb{N}^S$, $\bar{n} \neq \bar{0}$, we define for each $h, h=1, \dots, L$:

$$(h, \xi_1, \varphi_1) \prec_{\bar{n}} (h, \xi_2, \varphi_2) \quad \text{if } \xi_1 < \xi_2, \quad \text{or if } \xi_1 = \xi_2 \quad \text{and} \quad \varphi_1 > \varphi_2. \quad (4.16)$$

i.e., the vectors are ranked in increasing order as

$$(h, 0, \Psi_h^0), (h, 0, \Psi_h^0 - 1), \dots, (h, 0, 1), (h, 1, \Psi_{\ell(h)}^1), \dots, (h, 1, 1). \quad (4.17)$$

For each $\bar{n} \in \mathbb{N}^S$, $\bar{n} \neq \bar{0}$, there is an i with $n_i > 0$, and by definition of the polling table there exists an $h_n^- \in \{1, \dots, L\}$ such that $\ell(h_n^-) = i$. The subsets (4.17) of vectors (h, ξ, φ) are ranked with respect to the component h by increasing order of $h_n^- + 1, \dots, L, 1, \dots, h_n^-$, i.e., for all $\xi_1, \xi_2, \varphi_1, \varphi_2$,

$$\begin{aligned}
(h_1, \xi_1, \varphi_1) \prec_{\bar{n}} (h_2, \xi_2, \varphi_2) \quad \text{if } h_1 < h_2 \leq h_n^-, \quad \text{or if } h_n^- < h_1 < h_2, \\
\text{or if } h_2 \leq h_n^- < h_1. \quad (4.18)
\end{aligned}$$

By the definition of the Coxian distributions and the service discipline it follows that phase transitions without arrivals or departures of jobs are only possible to states with a higher order with respect to these

orderings, and that from each reachable state $(\bar{n}, h, \zeta, \varphi)$, $\bar{n} \neq \bar{0}$, there exists a path of states of increasing order with respect to $\prec_{\bar{n}}$ which leads with positive probability to a state $(\bar{n}, h_0, 1, 1)$ for some $h_0 \in \{1, \dots, L\}$ from which a departure is possible. Note that the state of highest order is $(\bar{n}, h_{\bar{n}}, 1, 1)$ and that this state is reachable by definition of $h_{\bar{n}}$. Based on the foregoing considerations the following power-series expansions can be introduced, cf. (2.5), for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\zeta=0, 1$, $\varphi=1, \dots, \Psi_h^0$ if $\zeta=0$, $\varphi=1, \dots, \Psi_{\ell(h)}^1$ if $\zeta=1$,

$$p(\bar{n}, h, \zeta, \varphi) = x^{n_1 + \dots + n_S} \sum_{k=0}^{\infty} x^k b(k; \bar{n}, h, \zeta, \varphi), \quad (4.19)$$

As indicated in section 2.4 the following set of equations follows from the balance equations (4.13), (4.14): for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$, $k=0, 1, \dots$,

$$\begin{aligned} \mu_h^{0, \varphi} b(k; \bar{n}, h, 0, \varphi) &= \mu_h^{0, \varphi+1} b(k; \bar{n}, h, 0, \varphi+1) I\{\varphi < \Psi_h^0\} \\ &+ \sum_{j=1}^S a_j \left[b(k; \bar{n} - \bar{e}_j, h, 0, \varphi) I\{n_j > 0\} - b(k-1; \bar{n}, h, 0, \varphi) I\{k > 0\} \right] \\ &+ \mu_{\ell(h-1)}^{1, 1} \pi_h^{0, \varphi} b(k-1; \bar{n} + \bar{e}_{\ell(h-1)}, h-1, 1, 1) I\{k > 0\} \left[1 - q_{h-1} I\{n_{\ell(h-1)} > 0\} \right] \\ &+ \mu_{h-1}^{0, 1} \pi_h^{0, \varphi} b(k; \bar{n}, h-1, 0, 1) I\{n_{\ell(h-1)} = 0\}; \end{aligned} \quad (4.20)$$

and for $\bar{n} \in \mathbb{N}^S$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_{\ell(h)}^1$, $n_{\ell(h)} > 0$, $k=0, 1, \dots$,

$$\begin{aligned} \mu_{\ell(h)}^{1, \varphi} b(k; \bar{n}, h, 1, \varphi) &= \mu_{\ell(h)}^{1, \varphi+1} b(k; \bar{n}, h, 1, \varphi+1) I\{\varphi < \Psi_{\ell(h)}^1\} \\ &+ \mu_h^{0, 1} \pi_{\ell(h)}^{1, \varphi} b(k; \bar{n}, h, 0, 1) + q_h \mu_{\ell(h)}^{1, 1} \pi_{\ell(h)}^{1, \varphi} b(k-1; \bar{n} + \bar{e}_{\ell(h)}, h, 1, 1) I\{k > 0\} \\ &+ \sum_{j=1}^S a_j \left[b(k; \bar{n} - \bar{e}_j, h, 1, \varphi) I\{n_j > 0\} - b(k-1; \bar{n}, h, 1, \varphi) I\{k > 0\} \right]. \end{aligned} \quad (4.21)$$

This set of equations (4.20), (4.21) forms a recursive scheme for all coefficients $b(k; \bar{n}, h, \zeta, \varphi)$ except those of states with $\bar{n} = \bar{0}$, because the equations (4.20), (4.21) express the coefficients $b(k; \bar{n}, h, \zeta, \varphi)$ in terms of

coefficients with a lower order, either with respect to the partial ordering $\prec$ defined in (2.7) or with respect to the orderings defined in (4.16) and (4.18). Hence, the only states which require further attention are states with $\bar{n} = \bar{0}$ and $\zeta = 0$. For these states the equations (4.20) read: for $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$, $k=0, 1, \dots$,

$$\begin{aligned} \mu_h^{0,\varphi} b(k; \bar{0}, h, 0, \varphi) &= \mu_h^{0,\varphi+1} b(k; \bar{0}, h, 0, \varphi+1) I\{\varphi < \Psi_h^0\} \\ &+ \mu_{h-1}^{0,1} \pi_h^{0,\varphi} b(k; \bar{0}, h-1, 0, 1) + y(k; h, \varphi); \end{aligned} \quad (4.22)$$

here, the quantities $y(k; h, \varphi)$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$, defined by $y(0; h, \varphi) := 0$ and for $k=1, 2, \dots$ by

$$\begin{aligned} y(k; h, \varphi) &:= \mu_{\ell(h-1)}^{1,1} \pi_h^{0,\varphi} b(k-1; \bar{e}_{\ell(h-1)}, h-1, 1, 1) \\ &- \sum_{j=1}^S a_j b(k-1; \bar{0}, h, 0, \varphi), \end{aligned} \quad (4.23)$$

consist of terms with coefficients of lower order with respect to $\prec$ than $(k; \bar{0}, h, 0, \varphi)$, cf. (2.7), and, hence, can be considered to be known. The sets of equations (4.22) are, for k fixed, dependent, as in the general case, cf. (2.8). The law of total probability gives, cf. (2.9),

$$\sum_{h=1}^L \sum_{\varphi=1}^{\Psi_h^0} b(k; \bar{0}, h, 0, \varphi) = \begin{cases} 1, & \text{for } k = 0, \\ -Z(k), & \text{for } k = 1, 2, \dots, \end{cases} \quad (4.24)$$

here, for $k=1, 2, \dots$,

$$Z(k) := \sum_{0 < n_1 + \dots + n_S \leq k} \dots \sum_{h=1}^L \sum_{\zeta=0}^1 \sum_{\varphi=1}^{\Psi_h^0} b(k - n_1 - \dots - n_S; \bar{n}, h, \zeta, \varphi). \quad (4.25)$$

Consider, for k fixed, the set of equations consisting of (4.24) and all but one of the equations (4.22). It is readily verified that the determinants $\Delta(k)$ of these sets of equations are independent of k and given by:

$$\Delta(k) = \Delta := \sigma_1 \prod_{h=1}^L \prod_{\varphi=1}^{\Psi_h^0} \mu_h^{0,\varphi}, \quad \text{for } k = 0, 1, 2, \dots \quad (4.26)$$

For $k=0$, this set of equations is readily solved: for $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$,

$$b(0; \bar{0}, h, 0, \varphi) = \frac{1}{\sigma_1 \mu_h^{0, \varphi}} \sum_{\psi=\varphi}^{\Psi_h^0} \pi_h^{0, \psi}. \quad (4.27)$$

It is more tedious, but straightforward, to show that for $k=1, 2, \dots$,

$$b(k; \bar{0}, L, 0, 1) =$$

$$\frac{-1}{\sigma_1 \mu_L^{0, 1}} \left[Z(k) + \sum_{h=1}^L \sum_{\varphi=1}^{\Psi_h^0} \frac{1}{\mu_h^{0, \varphi}} \sum_{\psi=\varphi}^{\Psi_h^0} \left\{ y(k; h, \psi) + \pi_h^{0, \psi} \sum_{j=1}^{h-1} \sum_{\nu=1}^{\Psi_j^0} y(k; j, \nu) \right\} \right]. \quad (4.28)$$

Once the coefficient $b(k; \bar{0}, L, 0, 1)$ has been determined according to (4.28), the other coefficients $b(k; \bar{0}, h, 0, \varphi)$, $h=1, \dots, L$, $\varphi=1, \dots, \Psi_h^0$, can be sequentially obtained with the aid of (4.22). Hence, relations (4.27), (4.20), (4.21), (4.28) and (4.22) form a complete scheme for computing the coefficients of the power-series expansions of the state probabilities.

4.5. Waiting times

Let W_j denote a random variable distributed as the stationary waiting time of jobs arriving at queue j , $j=1, \dots, s$. The number of jobs at queue j left behind by a job departing from that queue is equal to the number of jobs that arrived at queue j during the sojourn time of the departing job. Because arrivals occur according to a Poisson process, this implies, cf. Takagi [22],

$$E\{z^{N_j}\} = E\{e^{-\lambda_j(1-z)W_j}\} \chi_j(\lambda_j(1-z)), \quad |z| \leq 1, \quad j=1, \dots, s, \quad (4.29)$$

cf. (4.1). The moments of the waiting time distributions can be obtained from the moments of the marginal queue length distributions through these relations. The expected values of the waiting times for jobs in the various queues of a system with a cyclic polling order satisfy the following pseudo-conservation law, cf. Tediato [24],

$$\sum_{j=1}^s \left[1 - a_j(1-q_j) \frac{\sigma_1 x}{1-\rho} \right] n_j E\{W_j\} =$$

$$= \frac{\rho}{1-\rho} \frac{\beta_2}{2\beta_1} + \frac{\sigma_2}{2\sigma_1} + \frac{\sigma_1\rho}{1-\rho} \left[\sum_{j=1}^s \eta_j^2(1-q_j) + \frac{1}{2} \sum_{j=1}^s \eta_j(1-\eta_j) \right]. \quad (4.30)$$

here $\eta_j := \rho_j/\rho$ is the relative offered load at queue j , $j=1, \dots, s$. This relation provides a useful check on the accuracy of the computations. For systems with non-cyclic periodic order-of-visit rules a pseudo-conservation law is only known for the special case of exhaustive, gated and 1-limited number-of-services rules (i.e., $q_h=1$ or $q_h=0$, $h=1, \dots, L$, in the present model), with the restriction that queues with 1-limited service may be listed only once on the polling table, cf. Boxma et al. [10].

An important general property of the waiting times in systems with fixed polling orders is the following heavy traffic behaviour: for $j=1, \dots, s$, $E\{W_j\}$ and $E\{N_j\}$ tend to infinity as $\rho \uparrow 1$ if and only if, cf. (4.6), (4.10), (4.11),

$$a_j/m_j = \max_{i=1, \dots, s} \{a_i/m_i\}. \quad (4.31)$$

This implies that the modifications (2.18) and (2.19) for the initial sequence of the epsilon algorithm should only be applied to moments of distributions related to queues for which (4.31) holds. That only the arrival rates, and not the service rates, play a role in condition (4.31), can be explained by the fact that a certain (integer) number of jobs is served during each cycle of the server along the queues according to the polling table and the Bernoulli schedules. We will call service disciplines for which the mean waiting time at each station tends to infinity as the occupancy tends to one *balanced* disciplines. When the polling order for a system is fixed, then, in order that a discipline is balanced, the mean number of services attributed to the queues during one period must be such that

$$m_j : m_i = a_j : a_i, \quad \text{for } i, j = 1, \dots, s. \quad (4.32)$$

4.6. Example 1: a system with equally loaded stations

In this section the influence of the type of the service time distributions on the waiting times is studied. Four distributions will be considered, labeled A, B, C and D, each with mean $\gamma_{1j}=1$, $j=A, B, C, D$. Dis-

Table 1. Systems with 4 stations, with equal arrival rates, equal mean service times, cyclic polling, and equal switching rates between the stations: the influence of higher order moments of the service time distributions on the waiting time distributions.

System	DCP	$E\{W_A\}$	$E\{W_B\}$	$E\{W_C\}$	$E\{W_D\}$	$\sigma\{W_A\}$	$\sigma\{W_B\}$	$\sigma\{W_C\}$	$\sigma\{W_D\}$
ABCD	L	5.657	5.598	5.644	5.601	8.220	8.085	8.231	8.082
ABAB/CDCD	L	5.651	5.599	5.650	5.600	8.039	7.894	8.408	8.268
ACAC/BDBD	L	7.018	4.239	7.010	4.234	10.081	5.997	10.086	6.003
symmetric	L	7.014	4.236	7.014	4.236	9.867	5.855	10.295	6.142
ABCD	E	4.873	5.052	4.873	5.052	7.285	7.817	7.272	7.673
ABAB/CDCD	E	4.873	5.052	4.873	5.052	7.076	7.523	7.476	7.962
ACAC/BDBD	E	6.213	3.713	6.213	3.713	9.459	5.413	9.374	5.356
symmetric	E	6.213	3.713	6.213	3.713	9.172	5.219	9.655	5.545

tributions A and C have second moment $\gamma_{2j}=3$, $j=A,C$, and consist both of 2 phases; these distributions differ in the third moment: $\gamma_{3A}=15$, $\gamma_{3C}=20.25$. Distributions B and D have second moment $\gamma_{2j}=1.75$, $j=B,D$; distribution B consists of 4 phases, $\gamma_{3B}=3.98$, while distribution D consists of 3 phases, $\gamma_{3D}=6$. Table 1 shows the mean and the standard deviation of the waiting times in several 4-station systems. The arrival rates are equal, $\lambda_j=0.2$, $j=1,2,3,4$, and the switching times are identically, exponentially distributed, with $\sigma_1=0.1$, in all cases presented in the table. The stations have either all 1-limited service (L) or all exhaustive service (E), and the stations are visited in cyclic order. Under the heading "system" it is indicated that the system consists either of 4 stations with different service time distributions ("ABCD", visited in this order), or consists of 2 pairs of stations with different distributions ("ACAC/BDBD" indicates that the data for W_A and W_C stem from a system with 2 stations with distribution A and 2 stations with distribution C, visited in the order ACAC; and analogously for W_B and W_D), or consists of 4 stations with identical distributions ("symmetrical" indicates that the data for W_A stem from a system with 4 stations with distribution A; and analogously for W_B , W_C and W_D). It has been observed that the relative differences between W_A and W_C , respectively W_B and W_D , decrease when σ_1 increases. In the case of exhaustive service, the mean waiting times only depend on the first two moments of the service time distributions, as can be seen from the set of equations, given in Baker & Rubin [1] for general polling tables, which determine these quantities.

Table 2. Parameters and cost coefficients for a system with 4 stations.

j	λ_j	γ_{1j}	γ_{2j}	γ_{3j}	ρ_j	c_1	c_2	c_3	c_4	c_5
1	0.128	1.00	2.00	6.00	0.128	0.25	0.10	0.16	0.10	0.04
2	0.128	0.25	0.31	0.70	0.032	0.25	0.10	0.04	0.40	0.16
3	0.512	1.00	1.75	4.28	0.512	0.25	0.40	0.64	0.10	0.16
4	0.512	0.25	0.25	0.05	0.128	0.25	0.40	0.16	0.40	0.64

4.7. Example 2: various service disciplines for a 4-queue model

This section is concerned with a system consisting of 4 stations. The mean waiting times and several cost functions (weighted averages of the mean waiting times) have been computed for this system under various service disciplines. The five cost functions that we consider for this system are given by:

$$C_i := \sum_{j=1}^s c_{ij} E\{W_j\}, \quad i = 1, \dots, 5. \quad (4.33)$$

here the coefficients of the cost functions are defined by: for $j=1, \dots, s$,

$$\begin{aligned} c_{1j} &:= \frac{1}{s}, & c_{2j} &:= \frac{\lambda_j}{\lambda}, & c_{3j} &:= \eta_j = \frac{\rho_j}{\rho}, \\ c_{4j} &:= \frac{1}{\gamma_{1j}} \left[\sum_{k=1}^s \frac{1}{\gamma_{1k}} \right]^{-1}, & c_{5j} &:= \frac{\lambda_j}{\gamma_{1j}} \left[\sum_{k=1}^s \frac{\lambda_k}{\gamma_{1k}} \right]^{-1}. \end{aligned} \quad (4.34)$$

Cost functions C_1 , C_2 and C_3 are respectively station-, job- and load-weighted averages of the mean waiting times; cost functions C_4 , C_5 and C_2 are respectively station-, job- and load-weighted averages of the mean waiting times divided by the corresponding mean service times.

The parameters of the stations are listed in table 2. The service time distributions are exponential (station 1) or consist of 2 exponential phases, so that they are completely determined by their first 3 moments. First, we consider cyclic polling strategies: the stations are visited in the order 1,2,3,4. Usually, the order in which stations are arranged in a cycle has only a minor influence on the waiting times, cf. Blanc [4]. The switching times are identically, exponentially distributed, with $\delta_{1j}=0.05$, $j=1,2,3,4$, so that $\sigma_1=0.2$. Table 3 contains a list of Bernoulli schedules for this cyclic polling strategy, and the corresponding values of the mean waiting times and the cost functions can be found in table 4. The sched-

Table 3. Bernoulli schedules for the model of table 4.

DCP	q_1	q_2	q_3	q_4	x/ρ	DCP	q_1	q_2	q_3	q_4	x/ρ
Da1	1.00	0.00	0.00	0.00	1.1280	Db1	0.00	1.00	1.00	1.00	1.0320
Da2	0.00	1.00	0.00	0.00	1.1280	Db2	1.00	0.00	1.00	1.00	1.0320
Da3	0.00	0.00	1.00	0.00	1.1280	Db3	1.00	1.00	0.00	1.00	1.1280
Da4	0.00	0.00	0.00	1.00	1.1280	Db4	1.00	1.00	1.00	0.00	1.1280
Dc1	1.00	1.00	0.00	0.00	1.1280	Dc4	0.00	0.00	1.00	1.00	1.0320
Dc2	1.00	0.00	1.00	0.00	1.1280	Dc5	0.00	1.00	0.00	1.00	1.1280
Dc3	1.00	0.00	0.00	1.00	1.1280	Dc6	0.00	1.00	1.00	0.00	1.1280
Dd1	0.00	0.00	0.00	0.00	1.1280	Dd3	0.95	0.95	0.95	0.95	1.0064
Dd2	0.80	0.80	0.80	0.80	1.0256	Dd4	1.00	1.00	1.00	1.00	1.0000
De1	0.20	0.20	0.80	0.80	1.0256	De2	0.80	0.80	0.95	0.95	1.0064
Df1	0.20	0.80	0.20	0.80	1.1024	Df2	0.80	0.95	0.80	0.95	1.0256
Dg1	0.80	0.20	0.95	0.80	1.0256	Dg2	0.95	0.80	0.99	0.95	1.0064
Dh1	1.00	1.00	0.50	1.00	1.0640	Dh4	0.45	1.00	0.20	1.00	1.1024
Dh2	0.15	1.00	0.75	1.00	1.0320	Dh5	0.00	1.00	0.35	1.00	1.0832

Table 4. System with 4 stations with an offered load of $\rho = 0.80$ and with equal switching rates between the stations: cyclic polling order.

DCP	$E\{W_1\}$	$E\{W_2\}$	$E\{W_3\}$	$E\{W_4\}$	C_1	C_2	C_3	C_4	C_5
Da1	1.06	1.59	9.52	7.43	4.90	7.04	7.51	4.66	6.57
Da2	1.63	1.12	9.44	7.36	4.89	7.00	7.53	4.50	6.47
Da3	5.52	5.03	1.54	19.68	7.94	9.54	5.22	10.59	13.87
Da4	1.84	1.69	10.53	1.08	3.78	5.00	7.27	2.34	2.72
Db1	10.52	4.20	1.89	3.77	5.10	3.74	3.66	4.43	3.81
Db2	4.70	13.05	2.33	4.57	6.16	4.53	3.50	7.75	5.57
Db3	1.17	1.32	10.66	1.16	3.58	4.98	7.25	2.17	2.70
Db4	3.37	3.83	1.82	20.41	7.36	9.61	5.12	10.22	14.10
Dc1	1.06	1.20	9.53	7.44	4.81	7.02	7.51	4.51	6.52
Dc2	3.29	6.25	1.76	20.26	7.89	9.76	5.14	11.11	14.38
Dc3	1.17	1.80	10.64	1.15	3.69	5.01	7.25	2.36	2.77
Dc4	9.89	9.02	1.82	3.67	6.10	4.09	3.70	6.25	4.48
Dc5	1.86	1.23	10.55	1.08	3.68	4.96	7.27	2.16	2.65
Dc6	5.71	3.16	1.56	19.78	7.55	9.42	5.21	9.90	13.64
Dd1	1.62	1.50	9.43	7.35	4.98	7.02	7.53	4.65	6.52
Dd2	3.11	3.32	3.75	5.11	3.82	4.19	3.85	4.06	4.53
Dd3	4.28	4.77	2.87	5.06	4.24	4.07	3.52	4.64	4.63
Dd4	5.01	5.65	2.52	4.90	4.52	4.04	3.43	4.98	4.65
De1	5.39	5.03	3.33	4.51	4.57	4.18	3.92	4.69	4.44
De2	5.10	5.46	2.72	4.78	4.51	4.05	3.54	4.88	4.57
Df1	1.97	1.49	8.28	1.67	3.35	4.33	5.94	2.29	2.71
Df2	3.37	3.20	4.10	3.15	3.46	3.56	3.79	3.29	3.32
Dg1	4.20	8.11	2.35	7.26	5.48	5.08	3.66	6.80	6.49
Dg2	4.71	6.53	2.44	5.65	4.83	4.36	3.48	5.58	5.24
Dh1	1.80	2.03	6.18	1.74	2.94	3.55	4.60	2.31	2.50
Dh2	5.48	2.64	4.06	2.33	3.63	3.37	3.95	2.94	2.79
Dh4	1.79	1.45	8.40	1.27	3.23	4.19	5.92	2.11	2.46
Dh5	2.69	1.60	7.02	1.41	3.18	3.80	5.21	2.17	2.39

ules Da^* , Db^* , Dc^* , $Dd1$ and $Dd4$ are extremal in the space of Bernoulli schedules (q_1, q_2, q_3, q_4) , $0 \leq q_j \leq 1$, $j=1,2,3,4$. Intuitively, $E\{W_j\}$ is minimal for Da^* and maximal for Db^* over all Bernoulli schedules for cyclic polling orders. The Bernoulli probabilities are the same for each queue in the schedules Dd^* ; the schedules De^* and $Dd4$ are balanced disciplines, cf. (4.32). The schedules Df^* are such that the maximal mean visit time to queue j , $m_j \gamma_{1j}$, is the same for each queue ($j=1,2,3,4$). For the schedules Dg^* , the maximal mean number of services is proportional to the load of a queue, i.e., $m_i : m_j = \rho_i : \rho_j$, $i, j=1,2,3,4$. The schedules Dh^* have been determined by an extensive search. It is conjectured that cost function C_j is minimal over all Bernoulli schedules for the considered cyclic polling order for Dh^* , $j=1, \dots, 5$, where $Dh3=Dd4$. That the purely exhaustive discipline $Dd4$ is optimal for cost function C_3 is obvious from the pseudoconservation law (4.30). It is interesting to note that in Blanc [7] light traffic asymptotes of the mean waiting times have been determined by algebraic evaluation of the computation scheme of the p.s.a. for the special case of cyclic polling, exponential service times and negligible switching times. These asymptotes indicate that it is optimal in light traffic to take for cost function C_i , $i=1,2,4,5$,

$$q_j = 1, \text{ if } \eta_j < c_{ij}, \quad q_j = 0, \text{ if } \eta_j > c_{ij}, \quad j = 1, \dots, 4. \quad (4.35)$$

The numerical results for the present example with non-exponential service times and non-negligible switching times suggest that it is still optimal to take $q_j=1$ for queues $\eta_j < c_{ij}$, but that q_j should increase with increasing load for queues with $\eta_j > c_{ij}$, $j=1,2,3,4$. This is supported by the stability condition (4.10) which implies that the purely exhaustive discipline $Dd4$ will outperform any Bernoulli discipline for any system with cyclic polling when the offered load is sufficiently high, provided that all cost coefficients are positive.

Next, we consider more general periodic visit orders for the same system. Table 5 contains a list of polling tables and Bernoulli schedules. The schedules D^*B are balanced disciplines, cf. section 4.5. The Bernoulli parameters of stations which appear more than once on the polling table have been taken the same for each visit. For the discipline DkB we have also considered two variants: in discipline $DkBP$ the Bernoulli parameters of stations 3 and 4 are such that the proportion between the average maxi-

Table 5. Polling tables and Bernoulli schedules for the model of table 6.

DCP	table	q_1	q_2	q_3	q_4	q_5	q_6	q_7	q_8	x/ρ
DiB	132343	0.60	0.70	0.60	0.70	0.90	0.70			1.0192
DjB	13432343	0.60	0.60	0.80	0.60	0.60	0.60	0.80	0.60	1.0256
DkBP	134234	0.60	0.83	0.84	0.60	0.75	0.72			1.0192
DkBI	134234	0.60	0.75	0.89	0.60	0.83	0.20			1.0192
DkB	134234	0.60	0.80	0.80	0.60	0.80	0.80			1.0192
DlB	13432434	0.60	0.70	0.70	0.70	0.60	0.70	0.70	0.70	1.0256
DmB	31244213	0.80	0.20	0.20	0.80	0.80	0.20	0.20	0.80	1.0192
DnB	312421	0.90	0.20	0.20	0.90	0.20	0.20			1.0192
DoB	13422431	0.20	0.80	0.80	0.20	0.20	0.80	0.80	0.20	1.0192
DpB	134243	0.60	0.80	0.80	0.60	0.80	0.80			1.0192

Table 6. System with 4 stations with an offered load of $\rho = 0.80$ and with equal switching rates between the stations: non-cyclic polling orders.

DCP	$E\{W_1\}$	$E\{W_2\}$	$E\{W_3\}$	$E\{W_4\}$	C_1	C_2	C_3	C_4	C_5
DiL	3.61	3.22	3.16	42.23	13.05	18.84	9.49	18.86	28.19
DiB	5.87	5.85	2.76	5.32	4.95	4.40	3.79	5.33	5.01
DiE	6.04	6.53	1.93	6.07	5.14	4.46	3.43	5.84	5.48
DjL	5.91	5.27	3.30	14.17	7.16	8.11	5.54	8.70	10.68
DjB	6.63	6.69	2.99	4.30	5.15	4.25	3.93	5.36	4.57
DjE	6.91	7.94	1.92	4.96	5.43	4.24	3.45	6.04	5.03
DkL	3.17	2.86	6.81	5.32	4.54	5.45	5.83	4.27	5.08
DkLC	3.53	3.20	9.11	7.11	5.74	7.16	7.66	5.39	6.66
DkBP	6.02	6.13	2.98	4.11	4.81	4.05	3.78	5.00	4.33
DkBI	5.91	6.00	2.93	4.56	4.85	4.19	3.79	5.11	4.59
DkB	6.06	6.13	2.98	4.05	4.81	4.03	3.77	4.98	4.29
DkBC	6.52	6.59	3.17	4.30	5.14	4.30	4.02	5.32	4.58
DkE	6.39	7.23	2.19	4.41	5.06	4.00	3.42	5.52	4.59
DkEC	6.62	7.48	2.26	4.54	5.22	4.13	3.53	5.70	4.73
DlL	5.59	4.96	5.80	4.53	5.22	5.19	5.53	4.93	4.84
DlLC	6.33	5.63	6.97	5.44	6.09	6.16	6.57	5.75	5.75
DlB	6.71	6.71	3.12	3.76	5.08	4.09	3.94	5.17	4.25
DlBC	7.19	7.21	3.29	3.97	5.42	4.35	4.18	5.52	4.51
DlE	7.00	7.82	2.09	4.30	5.30	4.04	3.46	5.76	4.62
DlEC	7.23	8.10	2.14	4.39	5.46	4.15	3.55	5.93	4.74
DmL	1.60	1.62	7.09	5.81	4.03	5.48	5.79	3.84	5.17
DmB	4.90	4.81	3.19	4.81	4.43	4.17	3.79	4.66	4.55
DnL	1.07	1.11	21.81	16.98	10.24	15.73	16.89	9.52	14.57
DnD	1.82	1.83	7.03	7.12	4.45	6.02	6.00	4.47	6.05
DnB	4.63	4.57	3.30	5.31	4.45	4.36	3.89	4.75	4.84
DnE	3.86	4.78	2.84	5.66	4.28	4.26	3.53	4.85	4.99
DoL	1.84	1.87	7.04	5.69	4.11	5.46	5.79	3.91	5.14
DoB	5.28	5.30	3.04	4.68	4.58	4.15	3.75	4.82	4.54
DpL	3.15	2.86	6.80	5.52	4.58	5.53	5.85	4.35	5.20
DpD	2.17	2.17	6.98	5.64	4.24	5.48	5.80	4.04	5.16
DpB	5.91	6.05	2.94	4.50	4.85	4.17	3.79	5.11	4.56
DpE	5.82	6.81	2.11	5.63	5.09	4.36	3.45	5.77	5.26

mal duration of an intervisit time and that of the subsequent visit is the same for each visit, in DkBI they are such that the average maximal durations of the intervisit times are the same for each station. The schedules D*L and D*E are 1-limited ($q_h=0$, $h=1, \dots, L$) respectively exhaustive ($q_h=1$, $h=1, \dots, L$) disciplines with the same polling table as the corresponding discipline D*B. For all these disciplines the switching times between any pair of stations are identically, exponentially distributed with $\delta_{1j}=0.05$, $j=1, \dots, L$, so that $\sigma_1=0.05 \times L$, except for the scan-type disciplines Dm* and Do* where the switching times between two consecutive visits to the same station have been taken negligible small, so that $\sigma_1=0.3$ in these cases. The "end"-stations in the cases DmL and DoL have in fact a 2-limited service rule; for comparison, we have inserted disciplines DnD and DpD respectively, in which the "end"-stations have Bernoulli parameter 0.5 and the intermediate stations have 1-limited service. For the disciplines Dk* and D1* also a variant is considered in which it is assumed that the stations are arranged in a cycle and that the mean switching times between stations 1 and 3, respectively 2 and 4, are twice as long as those between the other, adjacent, pairs of stations; hence, $\sigma_1=0.4$ for the disciplines Dk*C and $\sigma_1=0.5$ for the disciplines D1*C.

5. Conclusions

A general framework for application of the p.s.a. has been described in section 2. The p.s.a. has been discussed in detail for a broad class of polling systems with periodic visit orders and Bernoulli schedules in section 4. Many polling systems with other service disciplines also fit in the general setting introduced in section 2. Examples are, cf. section 3, limited service (B3), cf. Blanc [7], and Markovian (A2) and dynamic (A4) order-of-visit rules. Another extension within the framework of section 2 consists of non-Poissonian arrival streams, but Coxian interarrival times have a strong impact on the size of the supplementary space Θ : the sizes indicated in (3.1)-(3.4) should be multiplied by the factors Ψ_j^a , the number of phases of the interarrival times at station j , for $j=1, \dots, s$. Other variants are models with finite buffers which require a few minor modifications, e.g., concerning the definition of the occupancy x , if all buffers are finite and the system is stable for any offered load, cf. Blanc [5]. Less straightforward generalizations of the algorithm are needed for

models with batch arrivals: then the birth-death structure is violated and the key property (2.3) does not hold. It seems to be possible to obtain a recursive set of equations by introducing power-series expansions as functions of some root of x in case of bounded batch sizes, but the applicability will be limited to small batch sizes because the required number of coefficient will grow very rapidly with the batch sizes. A better alternative might be to consider models with Markov modulated arrival processes, although they have a similar impact on the size of the supplementary space as Coxian interarrival times, while they disturb the recursive character of the computation scheme. A final extension of the p.s.a. which we mention here is the addition of migration to the processes, i.e., the admission of transitions to states $(\bar{n} + \bar{e}_j - \bar{e}_i, \psi)$, $i, j = 1, \dots, s$, $\psi \in \Theta$, $n_i > 0$, from a state $(\bar{n}, \varphi) \in \mathbb{N}^s \times \Theta$, which makes it possible to model networks of queues in which jobs may move from one queue to another queue. The computation scheme will only be recursive if the network is acyclic, as will be shown in a future paper.

References

- [1] Baker, J.E., I. Rubin. Polling with a general-service order table, *IEEE Trans. Commun.* COM-35 (1987), 283-288.
- [2] Blanc, J.P.C. A note on waiting times in systems with queues in parallel, *J. Appl. Probab.* 24 (1987), 540-546.
- [3] Blanc, J.P.C. On a numerical method for calculating state probabilities for queueing systems with more than one waiting line, *J. Comput. Appl. Math.* 20 (1987), 119-125.
- [4] Blanc, J.P.C. A numerical study of a coupled processor model, in: *Computer Performance and Reliability*, eds. G. Iazeolla, P.J. Courtois, O.J. Boxma (North-Holland, Amsterdam, 1988), 289-303.
- [5] Blanc, J.P.C. A numerical approach to cyclic-service queueing models, *Queueing Systems* 6 (1990), 173-188.
- [6] Blanc, J.P.C. The power-series algorithm applied to the shortest-queue model, Report FEW 379, Dept. of Economics, Tilburg Univ., 1989, to appear in: *Operat. Res.*, 1991.
- [7] Blanc, J.P.C. Cyclic polling systems: limited service versus Bernoulli schedules, Report FEW 422, Dept. of Economics, Tilburg Univ., 1990.
- [8] Blanc, J.P.C. The power-series algorithm applied to cyclic polling systems, Report FEW 445, Dept. of Economics, Tilburg Univ., 1990.
- [9] Boxma, O.J. Workloads and waiting times in single-server systems with multiple customer classes, *Queueing Systems* 5 (1989), 185-214.
- [10] Boxma, O.J., W.P. Groenendijk, J.A. Weststrate. A pseudoconservation law for service systems with a polling table, *IEEE Trans. Commun.* COM-38 (1990), to appear.

- [11] Boxma, O.J., J.A. Weststrate. Waiting times in polling systems with Markovian server routing, in: *Messung, Modellierung und Bewertung von Rechensystemen und Netzen*, eds. G. Stiege, J.S. Lie (Springer, Berlin, 1989), 89-104.
- [12] Brezinski, C. *Accélération de la Convergence en Analyse Numérique*. Lect. Notes in Maths. 584, Springer, Heidelberg, 1977.
- [13] Cohen, J.W. A two-queue model with semi-exhaustive alternating service, in: *Performance '87*, eds. P.-J. Courtois, G. Latouche (North-Holland, Amsterdam, 1988), 19-37.
- [14] Cohen, J.W. A two-queue, one server model with priority for the longer queue, *Queueing Systems* 2 (1987), 261-283.
- [15] Cooper, R.B. Queues served in cyclic order: waiting times, *Bell Syst. Techn. J.* 49 (1970), 399-413.
- [16] Hooghiemstra, G., M. Keane, S. van de Ree. Power series for stationary distributions of coupled processor models, *SIAM J. Appl. Math.* 48 (1988), 1159-1166.
- [17] Jaiswal, N.K. *Priority Queues*. Academic Press, New York, 1968.
- [18] Klimov, G.P., G.K. Mishkoy. *Priority Service Systems with Orientation*, Moscow Univ. Press, Moscow, 1979 (in Russian).
- [19] Kühn, P.J. Multi-queue systems with non-exhaustive cyclic service, *Bell Syst. Techn. J.* 58 (1979), 671-698.
- [20] Sarkar, D., W.I. Zangwill. Expected waiting time for non-symmetric cyclic queueing systems - exact results and applications, *Man. Sci.* 35 (1989), 1463-1474.
- [21] Servi, L.D. Average delay approximation of M/G/1 cyclic service queues with Bernoulli schedules, *IEEE J. Sel. Areas Comm. SAC-4* (1986), 813-822.
- [22] Takagi, H. *Analysis of Polling Systems*, The MIT Press, Cambridge MA, 1986.
- [23] Takagi, H. Queueing analysis of polling models: an update, in: *Stochastic Analysis of Computer and Communication Systems*, ed. H. Takagi (North-Holland, Amsterdam, 1990), 267-318.
- [24] Tediánto. Exact results for the cyclic-service queue with a Bernoulli schedule, *Performance Evaluation* 11 (1990), 107-115.
- [25] Wynn, P. On the convergence and stability of the epsilon algorithm, *SIAM J. Numer. Anal.* 3 (1966), 91-122.

IN 1989 REEDS VERSCHENEN

- 368 Ed Nijssen, Will Reijnders
"Macht als strategisch en tactisch marketinginstrument binnen de distributieketen"
- 369 Raymond Gradus
Optimal dynamic taxation with respect to firms
- 370 Theo Nijman
The optimal choice of controls and pre-experimental observations
- 371 Robert P. Gilles, Pieter H.M. Ruys
Relational constraints in coalition formation
- 372 F.A. van der Duyn Schouten, S.G. Vanneste
Analysis and computation of (n,N)-strategies for maintenance of a two-component system
- 373 Drs. R. Hamers, Drs. P. Verstappen
Het company ranking model: a means for evaluating the competition
- 374 Rommert J. Casimir
Infogame Final Report
- 375 Christian B. Mulder
Efficient and inefficient institutional arrangements between governments and trade unions; an explanation of high unemployment, corporatism and union bashing
- 376 Marno Verbeek
On the estimation of a fixed effects model with selective non-response
- 377 J. Engwerda
Admissible target paths in economic models
- 378 Jack P.C. Kleijnen and Nabil Adams
Pseudorandom number generation on supercomputers
- 379 J.P.C. Blanc
The power-series algorithm applied to the shortest-queue model
- 380 Prof. Dr. Robert Bannink
Management's information needs and the definition of costs, with special regard to the cost of interest
- 381 Bert Bettonvil
Sequential bifurcation: the design of a factor screening method
- 382 Bert Bettonvil
Sequential bifurcation for observations with random errors

- 383 Harold Houba and Hans Kremers
Correction of the material balance equation in dynamic input-output models
- 384 T.M. Doup, A.H. van den Elzen, A.J.J. Talman
Homotopy interpretation of price adjustment processes
- 385 Drs. R.T. Frambach, Prof. Dr. W.H.J. de Freytas
Technologische ontwikkeling en marketing. Een oriënterende beschouwing
- 386 A.L.P.M. Hendrikx, R.M.J. Heuts, L.G. Hoving
Comparison of automatic monitoring systems in automatic forecasting
- 387 Drs. J.G.L.M. Willems
Enkele opmerkingen over het inversificerend gedrag van multinationale ondernemingen
- 388 Jack P.C. Kleijnen and Ben Annink
Pseudorandom number generators revisited
- 389 Dr. G.W.J. Hendrikse
Speltheorie en strategisch management
- 390 Dr. A.W.A. Boot en Dr. M.F.C.M. Wijn
Liquiditeit, insolventie en vermogensstructuur
- 391 Antoon van den Elzen, Gerard van der Laan
Price adjustment in a two-country model
- 392 Martin F.C.M. Wijn, Emanuel J. Bijnen
Prediction of failure in industry
An analysis of income statements
- 393 Dr. S.C.W. Eijffinger and Drs. A.P.D. Gruijters
On the short term objectives of daily intervention by the Deutsche Bundesbank and the Federal Reserve System in the U.S. Dollar - Deutsche Mark exchange market
- 394 Dr. S.C.W. Eijffinger and Drs. A.P.D. Gruijters
On the effectiveness of daily interventions by the Deutsche Bundesbank and the Federal Reserve System in the U.S. Dollar - Deutsche Mark exchange market
- 395 A.E.M. Meijer and J.W.A. Vingerhoets
Structural adjustment and diversification in mineral exporting developing countries
- 396 R. Gradus
About Tobin's marginal and average q
A Note
- 397 Jacob C. Engwerda
On the existence of a positive definite solution of the matrix equation $X + A^T X^{-1} A = I$

- 398 Paul C. van Batenburg and J. Kriens
Bayesian discovery sampling: a simple model of Bayesian inference in auditing
- 399 Hans Kremers and Dolf Talman
Solving the nonlinear complementarity problem
- 400 Raymond Gradus
Optimal dynamic taxation, savings and investment
- 401 W.H. Haemers
Regular two-graphs and extensions of partial geometries
- 402 Jack P.C. Kleijnen, Ben Annink
Supercomputers, Monte Carlo simulation and regression analysis
- 403 Ruud T. Frambach, Ed J. Nijssen, William H.J. Freytas
Technologie, Strategisch management en marketing
- 404 Theo Nijman
A natural approach to optimal forecasting in case of preliminary observations
- 405 Harry Barkema
An empirical test of Holmström's principal-agent model that tax and signally hypotheses explicitly into account
- 406 Drs. W.J. van Braband
De begrotingsvoorbereiding bij het Rijk
- 407 Marco Wilke
Societal bargaining and stability
- 408 Willem van Groenendaal and Aart de Zeeuw
Control, coordination and conflict on international commodity markets
- 409 Prof. Dr. W. de Freytas, Drs. L. Arts
Tourism to Curacao: a new deal based on visitors' experiences
- 410 Drs. C.H. Veld
The use of the implied standard deviation as a predictor of future stock price variability: a review of empirical tests
- 411 Drs. J.C. Caanen en Dr. E.N. Kertzman
Inflatieneutrale belastingheffing van ondernemingen
- 412 Prof. Dr. B.B. van der Genugten
A weak law of large numbers for m-dependent random variables with unbounded m
- 413 R.M.J. Heuts, H.P. Seidel, W.J. Selen
A comparison of two lot sizing-sequencing heuristics for the process industry

- 414 C.B. Mulder en A.B.T.M. van Schaik
Een nieuwe kijk op structuurwerkloosheid
- 415 Drs. Ch. Caanen
De hefboomwerking en de vermogens- en voorraadaftrek
- 416 Guido W. Imbens
Duration models with time-varying coefficients
- 417 Guido W. Imbens
Efficient estimation of choice-based sample models with the method of moments
- 418 Harry H. Tigelaar
On monotone linear operators on linear spaces of square matrices

IN 1990 REEDS VERSCHENEN

- 419 Bertrand Melenberg, Rob Alessie
A method to construct moments in the multi-good life cycle consumption model
- 420 J. Kriens
On the differentiability of the set of efficient (μ, σ^2) combinations in the Markowitz portfolio selection method
- 421 Steffen Jørgensen, Peter M. Kort
Optimal dynamic investment policies under concave-convex adjustment costs
- 422 J.P.C. Blanc
Cyclic polling systems: limited service versus Bernoulli schedules
- 423 M.H.C. Paardekooper
Parallel normreducing transformations for the algebraic eigenvalue problem
- 424 Hans Gremmen
On the political (ir)relevance of classical customs union theory
- 425 Ed Nijssen
Marketingstrategie in Machtsperspectief
- 426 Jack P.C. Kleijnen
Regression Metamodels for Simulation with Common Random Numbers: Comparison of Techniques
- 427 Harry H. Tigelaar
The correlation structure of stationary bilinear processes
- 428 Drs. C.H. Veld en Drs. A.H.F. Verboven
De waardering van aandelenwarrants en langlopende call-opties
- 429 Theo van de Klundert en Anton B. van Schaik
Liquidity Constraints and the Keynesian Corridor
- 430 Gert Nieuwenhuis
Central limit theorems for sequences with $m(n)$ -dependent main part
- 431 Hans J. Gremmen
Macro-Economic Implications of Profit Optimizing Investment Behaviour
- 432 J.M. Schumacher
System-Theoretic Trends in Econometrics
- 433 Peter M. Kort, Paul M.J.J. van Loon, Mikulás Luptacik
Optimal Dynamic Environmental Policies of a Profit Maximizing Firm
- 434 Raymond Gradus
Optimal Dynamic Profit Taxation: The Derivation of Feedback Stackelberg Equilibria

- 435 Jack P.C. Kleijnen
Statistics and Deterministic Simulation Models: Why Not?
- 436 M.J.G. van Eijs, R.J.M. Heuts, J.P.C. Kleijnen
Analysis and comparison of two strategies for multi-item inventory systems with joint replenishment costs
- 437 Jan A. Weststrate
Waiting times in a two-queue model with exhaustive and Bernoulli service
- 438 Alfons Daems
Typologie van non-profit organisaties
- 439 Drs. C.H. Veld en Drs. J. Grazell
Motieven voor de uitgifte van converteerbare obligatieleningen en warrantobligatieleningen
- 440 Jack P.C. Kleijnen
Sensitivity analysis of simulation experiments: regression analysis and statistical design
- 441 C.H. Veld en A.H.F. Verboven
De waardering van conversierechten van Nederlandse converteerbare obligaties
- 442 Drs. C.H. Veld en Drs. P.J.W. Duffhues
Verslaggevingsaspecten van aandelenwarrants
- 443 Jack P.C. Kleijnen and Ben Annink
Vector computers, Monte Carlo simulation, and regression analysis: an introduction
- 444 Alfons Daems
"Non-market failures": Imperfecties in de budgetsector
- 445 J.P.C. Blanc
The power-series algorithm applied to cyclic polling systems
- 446 L.W.G. Strijbosch and R.M.J. Heuts
Modelling (s,Q) inventory systems: parametric versus non-parametric approximations for the lead time demand distribution
- 447 Jack P.C. Kleijnen
Supercomputers for Monte Carlo simulation: cross-validation versus Rao's test in multivariate regression
- 448 Jack P.C. Kleijnen, Greet van Ham and Jan Rotmans
Techniques for sensitivity analysis of simulation models: a case study of the CO₂ greenhouse effect
- 449 Harrie A.A. Verbon and Marijn J.M. Verhoeven
Decision-making on pension schemes: expectation-formation under demographic change

- 450 Drs. W. Reijnders en Drs. P. Verstappen
Logistiek management marketinginstrument van de jaren negentig
- 451 Alfons J. Daems
Budgeting the non-profit organization
An agency theoretic approach
- 452 W.H. Haemers, D.G. Higman, S.A. Hobart
Strongly regular graphs induced by polarities of symmetric designs
- 453 M.J.G. van Eijs
Two notes on the joint replenishment problem under constant demand
- 454 B.B. van der Genugten
Iterated WLS using residuals for improved efficiency in the linear
model with completely unknown heteroskedasticity
- 455 F.A. van der Duyn Schouten and S.G. Vanneste
Two Simple Control Policies for a Multicomponent Maintenance System
- 456 Geert J. Almekinders and Sylvester C.W. Eijffinger
Objectives and effectiveness of foreign exchange market intervention
A survey of the empirical literature
- 457 Saskia Oortwijn, Peter Borm, Hans Keiding and Stef Tijs
Extensions of the τ -value to NTU-games
- 458 Willem H. Haemers, Christopher Parker, Vera Pless and
Vladimir D. Tonchev
A design and a code invariant under the simple group Co_3

Bibliotheek K. U. Brabant

17 000 01086042 8